TOYOTA EPC SYSTEM Install Manual

2016.1

TOYOTA MOTOR CORPORATION

Index

	1
	2
	4
	6
	8
	8
	19
	26
	27
	28
	34
	37
	38
	40
	40
	51
•••••	58
	59
	60
•••••	63
•••••	69
•••••	72
•••••	72
•••••	74
	82
	87
	88
	89
	90

4. EPC Functions To Be Localized By Users		93
4 – 1 . Price File Setup .		94
4 – 2. Locally Supplied Parts Setup .		96
4 – 3. Starting EPC System from Another Application		99
4 – 4 . Another Interface Application Setup		101
4 – 5 . Group Setup		115
4 – 6 . Screen / Message box language		120
5. For Distributors		124
6. EPC System Setup File Copy		136
7. Dealing with Failures	•••••	139

1. System Requirements

1-1-1. What is standalone type?

• This type directly sets up the new electronic catalog data to PC's hard disk. Set up the DVD data to your own terminal, and read the data in your own terminal from the program (see [p.6] for details of the setup).

1-1-2.System requirements

ITEM	MODEL	NOTE
PC	IBM AT-BUS Compatible Model	Supporting Windows family*3 Memory : 64MB or more H/D : *5 Display : 1024 × 768 Pixels or higher-resolution*6
DVD Drive	Not specified	Supporting Windows family*3
Printer	Laser Printer Only	Supporting Windows family*3 (Not supported Line Printer)
Operating S/W	Windows family*3	

*3) Windows family

: Windows 98/2000/XP/Vista/7(32bit)/8(32bit)

*6) Windows7

: 1280 × 1024 Pixels

Hard disk capacity

	USE	NECESSARY H/D CAPACITY
OS operation		Suitable
EPC operation	DVD Data from DVD Drive	100MB per 1 Spec.
	DVD Data in H/D (4.7GB per 1DVD)	a) Initial: 100MB or more b) Catalogue DVD: 3.0GB per 1 Spec. c) Frame No. DVD: 3.0GB per 1 Spec.
Local data (Price/L	ocally Supplied P/No.)	Suitable

*5) Hard disk capacity for Standalone to run EPC (+ +)

(Example) DVD Data for Europe spec.(A1) and Frame No. on Hard disk

: Suitable : a)+b)+c) = (More than 100MB)+3GB+1.5GB = More than 4600MB : Suitable + + = Necessary H/D capacity 1-1-3. Basic Configuration for EPC Windows 2000



1-2-1. What is Server / Client type?

• This type performs the data setup by preparing the server specifically for the new electronic catalog, and read the data in the server from the client.

Approx. 10 clients is allocated for one server under the same building, and the number of the server is decided according to the number of clients (see [p.37] for details of the setup).

* Clients need to install PGM, but the data setup is not required.

ITEM	·	MODEL	NOTE
РС	Server	IBM AT-BUS Compatible Model	Supporting Windows Server family*1 Memory : 96MB or more H/D : *2 Display : 1024 × 768 Pixels or higher-resolution
	Client .	IBM AT-BUS Compatible Model	Supporting Windows family*3 Memory : 64MB or more H/D : *4 Display : 1024 × 768 Pixels or higher-resolution *6
DVD Drive	Server .	Not specified	Server must equip at least one DVD drive supporting Windows Server family*1
	Client	Not specified	Not necessary for EPC
Printer	Server	Laser Printer Only	Supporting Windows Server family*1
	Client	Not specified	Not necessary for EPC
Operating S/W	Server	Windows Server family*1	
	Client	Windows family*3	

1-2-2.System requirements

*1) Windows Server family : 2000Server/XP Professional/2003Server

*3) Windows family : Windows 98/2000/XP/Vista/7(32bit)/8(32bit) : 1280 × 1024 Pixels

*6) Windows7

Hard disk capacity

	US	E	NECESSARY H/D CAPACITY
Server	OS operation (Win	dows Server family*1)	Suitable
	EPC operation	DVD Data in H/D (*4.7GB per 1DVD)	a) Initial: 100MB or moreb) Catalogue DVD: 3.0GB per 1 Spec.c) Frame No. DVD: 3.0GB per 1 Spec.
	Local data (Price/L	ocally Supplied P/No.)	Suitable
Client	OS operation (Win	dows family*3)	Suitable
	EPC operation		100MB or more

*2) Hard disk capacity for Server PC to run EPC (+ +)

*4) Hard disk capacity for Client PC to run EPC (+)

.

1-2-3.Basic Configuration for EPC Windows 2000 & 98 Clients



2. Setup Procedure of Standalone Type



When updating program

EPC Program Renewal (2-2-5 : p.28)

When recovering program

EPC Program Recovery (2-2-6:p.34)

2-2-1.EPC Program Install

(1)Opening Windows and inserting a A1DVD to the DVD drive.



- * Turn on your computer to open a Windows.
- * After the Windows is start up, insert the A1DVD to the DVD-ROM drive.
- * Right-click the "My Computer" on the desktop and left-click the "Explore".



(2)Running the install system from a A1DVD.



- * Left-click the drive where you have set the A1DVD.
- * Double-click the "setup.exe".
- * Do not use "Thumbnails" for the display of icons.

Go on to the next page

(3)Starting the Installation



- * To execute the TOYOTA EPC Install, left-click the "Next" button.
- * To cancel the installation, left-click the "Cancel" button.
- * A message for asking if you cancel the installation or not will appear again. Click the "OK" button to cancel the installation or click the "Cancel" to continue.

(4)Selecting a drive for the installation.



- * Select the drive where you want to install the TOYOTA EPC, and left-click the "Next" button.
- * To cancel the installation, left-click the "Cancel" button.
- * If installing for the first time, go to (6) [Selecting a system configuration].

Go on to the next page

(5)Checking the Install Configuration [Some install configurations may have the following A) or B) case.]

A)In case that the EPC is already installed,



- * To install it again, left-click the "Next" button to transit to (7) [System Installation].
- ** Even if a new system is already installed, another installation will maintain the existing setup information.
- * To go back to the previous screen(4) [Selecting a drive for the installation], leftclick the "Back" button.
- * To cancel the installation, left-click the "Cancel" button.

B)In case that the disk space isn't enough,

puter	TOYOTA ELECTRONIC PARTS CATALOG DISTALL 22	l
nosh s Ban Re Re	The excitabilities of a disk are exactlineed. Installation corrying cut the minimum 10240MB is required) in order to stop installation, please click [Cancellation]	
	Carcel	

- * The EPC installation needs the disk space of 10 MB.
- * To change the drive for the installation, leftclick the "Back" button to go back to the previous screen (4) [Selecting a drive for the installation].
- * To cancel the installation, left-click the "Cancel" button.

(6)Selecting a system configuration



- * Select a system configuration ("Standalone"), and left-click the "Next" button.
- * To cancel the installation, left-click the "Cancel" button.

(7)System Installation



* Wait for a while until the installation from the DVD has been completed.

Go on to the next page

(8)Copying a setup file



- * If there isn't the copy of the setup file, select the "No" and left-click the "Next" button to transit to (11) [Setting a background image].
- * If there is the setup file, select the "Yes" and left-click the "Next" button to transit to (9) [Selecting the drive where the setup file is inserted].

See (p.137) for the setup file copy

(9)Selecting the drive where the setup file is inserted.



- * Insert a floppy with the setup file to the floppy drive, select the drive where you inserted the floppy, and then left-click the "Next" button.
- * To cancel the copy of the setup file, left-click the "Back" button to go back to the previous screen (8) [Copying a setup file].
- ** In the case that a correct floppy drive or a floppy with a correct setup file isn't setup, an error message of "An applicable file is not found." will appear. You should setup it again correctly.

(10)Copying a file



* Wait for a while until the setup file has been copied from the floppy.

(11)Setting a background image



- * If you setup the default background image to this EPC screen, select the "No" and left-click the "Next" button to transit to (13) [Completing the installation].
- * If you want to setup the background image of your own choice to this EPC screen, select the "Yes" and left-click the "Next" button to transit to (12) [Selecting a background].

What is background image?

You can display the image you prefer as background of the menu screen.

(12)Selecting a background image



- * To setup the background image to the Main Menu, left-click the "browse" button and select a file, then left-click the "Next" button.
- * To setup the background image to other than the Main Menu, left-click the "browse" button and select a file, then left-click the "Next" button.
- ** The file types of JPEG, BMP,and PNG can be selected as a background image.
- * To go back to the previous screen (11) [Setting a background image], left-click the "Back" button.

(13)Completing the installation



- * As the EPC installation is completed, left-click the "Finish" button.
- ** When the installation is complete, extract the A1DVD from the DVD-ROM drive.

Go on to the next page

When having used the 2007 version of this New EPC, please kindly follow the following procedure of (14) and (15). When newly using the 2008 version of this New EPC, you do not need to follow the procedure of (14) and (15).



(14)Deleting number information of the old frames

* Right-click the "My Computer" on the desktop and left-click the "Explore".





* Left-click the drive where the data is set up.

* Left-click the "TMCEPCW3" folder.



* Left-click the "epcdata" folder.

No. Dial mare Powerke
Address D.D.1993201/Sciences Processor X Name - Ison Trape Date Notice In Decision Inf. The Trade List Science Inf. Inf. Processor List Science Inf. Inf. Processor List Science Inf. Inf. Processor List Science Inf. Processor Inf. Processor Inf. Processor Inf. Processor Inf. Processor Processor List Science
Address D 1970;3710;47(accoding) Problem X Name - Name D set Address IP Tools
Prefere X Name Name Date Date <thdate< th=""> Date Date <</thdate<>
Image: Section of the sectio
C (0.0000) C (0.0000) C (0.000) C (0.000
a Ta Construct 21

* Left-click the "FL" folder.

(15) Deleting the folders OV1-OV5



- * If the folders "OV1"-"OV5" exist, delete them with Shift+Delete.
- ** If the "OV" folder already exists, do not delete this folder.

(16)Starting the TOYOTA EPC SYSTEM



*Insert the A1DVD to the DVD drive.

* Double-click the "TOYOTA EPC SYSTEM" on the desktop to start the TOYOTA EPC SYSTEM.

*If using the current EPC group setup file...

Setup procedure

1.Copy the Group Setup Files to the Floppy Disk. (Group Setup Files: <u>TMCMSTW2¥GCGRPMEI.D</u> and <u>TMCMSTW2¥GCGRPPNC.D</u>) 2.See (8) [Copying a setup file] on (p.12).

*If you want to uninstall EPC...

In PC drive where EPC program is installed, delete 'TMCEPCW3' folder. And delete EPC shortcut icon on the desktop.

2-2-2.EPC Data Setup

(1) Data environment setup

* Press Setup Menu.





* Data Configuration	: Setups Data Operation(DVD/Hard Disk/Server). Run this setup first after the EPC system is installed.
* Data Setup	: Setups the data with the contents created on the [Data Configuration] screen. This setup must be run whenever the data is update.
* Area/Language Setup	: Setups Data Language and Screen Language. Select an Area when the data of multiple Areas are setup.
* Group Setup	: Catalog Codes and Part Name Codes which are often searched should be registered here so that you can search the data by Group Code.
* Screen File Setup	: Use when changing a displayed title on the screen.
* Setup File Copy	: The setup Environment can be copied on other computers It will be helpful to operate multiple computers under the same environment.
* Locally Supplied Parts Setup	: Setup the data here when searching for Locally Supplied Parts.
* Price File Setup	: Setup the data here when searching Price File.
* Another Interface Application Setup	: Use when operating another system using the search results on EPC system.
* LEXUS Dealer Check	: Lexus Dealer must enter a given password so that you can search Lexus catalog.
** Clicking the "Menu" button ends t	he Setup Menu and goes back to the Main Menu.

(2) Entering Sales Area Code

	Per Ho	Dete	The Southe of Copy	Ovtput
Factor	A.1			9 2
General .	42			
HIA, Canada Japap	81		•	
Cubat C	14			
	83		•	
	84			1
	85			
	-			
	-			
	Fee Bu	Data	The Bourte of Copy	Output
Oversess	13			
Japan	72	1		
	13		•	
	74			
	78			al .
	1.1			
	n p	7		
	11	1		
Adres Break Car	PT	2ete	The Bruce of Stpy	Owasia
5	PT Dect No TL	2ete	The Bruce of Stpy	Output
	PT	2ete	The Service of Supp	Section Section
	FT Sec No R1 R3	2ete	The Bruce of Stpy	Output

- * In order to search substitution part number/procurement part number corresponding to the region, enter the 5-digit Sales Area Code.
- * Sales Area Code will be described separately.
- * The ticked product numbers will not be searched.
 - If "Procr" is ticked, the procurement part number will not be displayed.
 - If "Subs" is ticked, the substitution part number will not be displayed.

(3) To setup the operation for EPC (Catalog) data





- * Select the Area you want to setup. Select the type of DVD (Area) you want to set.
- * Setup the EPC data here. Select the Area you want to setup, and setup the method for operating and the recorded place of the data for each Rec#.
- * Setup the method of your operation. Select a CD-ROM/HardDisk /Server from a pull-down list box.
- ** When installed with "Standalone" or "Server", you can select only "HardDisk". When installed with "Client", you can select only "Server".

Anna	Per No	Dete.	The los	and of Copy Output	
Europe	A1	Bac 421.48	-	-	1
General	42		1		
HIA, Canada Japan	81		· 24		2
Subao	84		 I 		2
	83		• G s		2
	84		- mi		
	85		N		
	1000		N		
	-		Arbites		
A++	Ber Bu	Data	The Buy	ane of Copy Output	
Overseas	P3	-	-1		
Japan	72		2	2	
	73		• 1	-	-
	74		*	2	
	75		1	-	2
	74	-		-	
	11		-		
		7			
	and the second second			and the second second	
Sales Rest Code	Sec No.	Date	The Se	upoe of Copy Sungua	
100000	81		2	-	
	#2		1		
184	81			-	
C Proc.	Local File		1	2	
	Frice File			*	

- * Select the drive where the catalogue data is set.

Area	Fee Ho	Date	The Buasts of Copy	Output -
Earspe	41	Bar (D-1.88)		
Oeneral Hik/Canada	42		3	
Japan .	21		2	¢†
10000	81		2 2	24
	13		2 2	N / I
	24	1		
Concession in which the Party number of the Pa	91		21 2	21
				T
				21
Area	Rec Bo	Data	The fourne of Copy	Out put 2
Oversear	71	1	-	
Zagasi .	72		-	
	13		2 2	
	74		-	
	11			
	71	-		
·	17		3	
	12.12.12			
Sales Read Code	Sec Bo	Date	The Bourne of Copy	Output
22220	F1		-	
	81		-	•
180	#1		-	
Proce	Local File		1	
17 has	frice file		2	

- * In the case that the Hard Disk is set, select a drive where the data is copied.
- ** In case of the Server, you can't set the drive.

(4) To setup the operation for EPC (FrameNo) data

Ans Per Ho Data The House at Copy Output General A1 Parability Pr
Area Area <th< td=""></th<>
And Japan Jack
B3 B
No.
Ref Dist Dist <thdist< th=""> Dist Dist D</thdist<>
In Image: Second s
Ans December of Copy De
Destination Fit Date is the second of the s
Destination Fit Date is the second of the s
Over sees r1 Pacubisk Pi Z 72 3 2 2 2 73 3 2 2 2 74 3 2 2 2 74 3 2 3 2 74 3 2 3 2 74 3 3 3 3 74 3 3 3 3 74 3 3 3 3 74 3 3 3 3 74 3 3 3 3 74 3 3 3 3 74 3 3 3 3 74 3 3 3 3 74 3 3 3 3 74 3 3 3 3 74 3 3 3 3 74 3 3
Pages F2 N N 77 0 0 0 76 0 0 0 76 0 0 0 76 0 0 0 76 0 0 0 71 0 0 0 71 0 0 0 71 0 0 0 72 0 0 0 72 0 0 0
F4 2 2 4 F4 2 3 71 F4 2 3 61 F4 2 3 61 F4 2 3 61 F1 2 3 71 F1 2 3 71 F2 7 7 7 71 F2 7 7 7 71 F3 7 7 7 71 F3 7 7 71 71 71 F3 7 7 71
P4 2 2 4 P3 2 3 71 P4 2 3 61 P4 2 3 61 P1 2 3 61 P1 2 3 71 P2 3 3 71 P2 2 2 71 P2 2 71 7 P2 7 7 7 7 7 P2 <td< td=""></td<>
PS P
The Brace of City Setup Ri Single Set Set Set Set Set Set Set Set Set Se
The Brace of City Setup Ri Single Set Set Set Set Set Set Set Set Set Se
The Brace of City Setup Ri Single Set Set Set Set Set Set Set Set Set Se
N
Bit
Front Local Fale
Frank Prite E

- * Perform the same operation about FrameNo DVD
- ** As the number becomes bigger, the frame information will be newer. (F1 is the oldest DVD.)

(5) To setup the operation for JPIO, Local File, and Price File



 \square

- * Perform the same operation about JPIO, Local File and Price File as well.
- ** As for Local File and Price File, only operation method (HardDisk only) and the Output place can be selected.
 The actual data should be set on the [Locally Supplied Parts Setup] and [Price File Setup] screen.
- ·Setup J-PIO to M1
- ·See (p.96) for Locally Supplied Parts Setup
- See (p.94) for Price File Setup

Anna	Per Bu	Dete		The Bourne of Copy	Overgrant	
Europe	41	Bar 42 Lak			84.	
General	42		•			
Hik, Canada	81	-				
Labou	14	-				
	10					
	84	-				
	85	-			1	- Internet
	a start a				-	
	-					
Contraction of the	Ber Bo	Data	_	The Buards of Copy	Output	-
Oversess	11	Par di 1 sk	*1		19±	
Japan	12		•			
	11	-				
	74	1	•		1	
	75	-				-
	F1	-			1	
	12	1				
		7		I DESCRIPTION OF		
	(Kennelson)			in the second second second	CALLER A.	
Sales Beas Lode	Sec No	2ata		The Boucee of Copy	C Changelan	
00000	#1	Rec (D) LAK	2	(F)	2 21	
and the second s	12				1	
100	R1	2.			<u>.</u>	
C Proc.	Local file	BWC GELER	-		-	
Pines	Frite File	Bog (D) Leit			-	
					+	
	Please c	holde the appropriate	FPC CI	Yis) while want to use		
A DESIGN A D	The second	100 C	A		GENUE	
12	- XX			BysCarda	Entropy 1	

* After you set the data environment, click the "Exec" button.



- * Click the "OK" button.
- * Click the "Menu" button to return the "Setup Menu".

(6) Data Setup





- * The setup Information on the setup Area is displayed.
- * Select an Area.
- Select a Rec# of the data .
- You can select multiple Rec#s.
- ** If an Area or a Rec# you want to setup isn't listed, setup the environment on the [Data Configuration] screen.





* After you select the Rec#, click the "Exec" button. DVD confirmation message will be displayed.

Set the corresponding DVD.

- ** When the setup is complete, the date of the data will be updated.
- ** When setting up the data for several Areas, change the Area and select the Rec#.



- * When the setup is complete, dialog is displayed. And then click the "OK" button.
- ** If you want to setup other Area, repeat the same operation.After all setup is complete, click the "Menu" button to go to the "SETUP MENU".
 - If the operation is performed by DVD-ROM, do not remove the DVD until returning to the main menu after the setup.

2-2-3.Area / Language Setup

The Area you want to search on the EPC system and the Screen Language can be selected.

-Area	: The Area which has setup on the [Data Setup] screen can be selected.
	The Area which is selected here is searched.
-Data Language	: When the data such as Part Names, Illustration Name etc, is provided by each
	language, the Language Data which is selected here is displayed.
-Screen Languag	e : The contents on the screen are written in the Language which is selected here.

Please select "Area/Language Setup" of "SETUP MENU".



2-2-4.LEXUS Dealer Check



- * In order to use the LEXUS catalog, you need the LEXUS password.
- * Click the "LEXUS Dealer Check" button.
- ** In case of client, you cannot click "LEXUS Dealer Check" button.If it is set at the server, searching the LEXUS catalog from the client becomes possible.

- * Enter a LEXUS Password and click the "Exec" button.
 - The only right password allows you to use this LEXUS Catalog.

To clear the displayed contents ;

unctus Back friet	inte		O FORD IL COLLE DAMA	-
	Passweet	1		
Enter th	e LEXUS dealer pas	ssword given for th	is set of CDs and pre	tta Fill key
second in comparison of the local division of the	successive in successive successive of the	and the second se	summer of the local division of the local di	COLUMN TWO IS NOT

* Click the "Clear" button to delete the displayed data.

2-2-5. Procedure of Program Renewal by A1DVD

1. Program Renewal Message

The message appears on the screen if the new program exist in it when setting up A1DVD. In this case, please implement renewing the latest program by referring to "Program renewal by A1DVD"

(1) Checking the program renewal message

1. EPC Data Setup



* Setup EPC data according to the normal procedure.

2. The EPC installation is completed



* When the setup is completed, a dialog is displayed. Please click the "OK" button.

3. Checking the program renewal message



Check the new version, and then Left-click on the "OK" button.



The program is not renewed automatically just by pressing the "OK" button. Please implement renewing the program by referring to "Program renewal by A1DVD".

2 .Program Renewal by A1DVD



Please end "TOYOTA EPC SYSTEM" if it is activating to you renew the program by A1DVD.

(1)EPC the Latest (EPC) Program Update

1.EPC the Latest Program Update-1



2.EPC the Latest Program Update-2



* Left-double-click " DVD-ROM Drive"

3.EPC the Latest Program Update-3



* Left-double-click the " APLI" folder

* Left-double-click "Apli_Copy.bat"

4.EPC the Latest Program Update-4

lie Edit View Pavorites Too				
3 tot - 10 3 1	Search 🕑 Pokkers 🛄+			_
LINALS CHARLE				
Pile and Folder Tasks A Browner the file Tops the file Copy the file Tops the file Didate file Tops the file Didate file Tops the file Didate file Tops the file	Neg - CPOH CPOH CONSTRUCTION CONSTRUCTION NOPDer Sean or NOPDer Sean or NOPDer Sean or NOPDer Sean or NOPDER NOPDER Sean of the Sean of th	See Tryse File Folder 4x8. McS-Gold Batch 8,643.88. Application	Data-Modified 10(27)2000 6-00 PH 10(27)2000 6-00 PH 10(27)2000 6-00 PH 10(27)2000 6-00 PH	Dato Picha
Mr Gozzmelte Mr Go				

5.EPC the Latest Program Update-5



* A message appears,"Input the destination drive where EPC has been installed"

Input the destination drive where EPC has been installed, then press "Enter" key.

If you inputted the drive where EPC is not installed, input it again correctly. Then press the "Enter" key.

6.EPC the Latest Program Update-6

C:\WINDOWS\System32\cmd.exe	- D ×	Wait for a while .
. APLI BRX-translations.doncata_B3.ts .APLI BRX-translations.doncata_B4.in .APLI BRX-translations.doncata_B4.en .APLI BRX-translations.doncata_B4.en .APLI BRX-translations.doncata_B5.in .APLI BRX-translations.doncata_B5.in .APLI BRX-translations.doncata_B5.ts .APLI BRX-translations.doncata_B5.ts .APLI BRX-translations.doncata_97.ts .APLI BRX-translations.doncata_97.en .APLI BRX-translations.doncata_97.ts .APLI BRX-translations.doncata_97.ts .APLI BRX-translations.sec08-sjis.in1 .APLI BRX-translations.sec08-sjis.in1 .APLI BRX-translations.sec08-sjis.in1 .APLI BRX-translations.sec08-sjis.in1 .APLI BRX-translations.sec09-sjis.in1 .APLI BRX-translations.sec09-sjis.in1 .APLI BRX-translations.sec09-sjis.in1 .APLI BRX-translations.sec09-sjis.in1 .APLI BRX-translations.sec09-sjis.in1 .APLI BRX-translations.sec09-sjis.in1 .APLI BRX-translations.sec09-sjis.in1 .APLI BRX-translations.sec09-sjis.in1 .APLI BRX-translations.trans01.ini .APLI BRX-translations.trans01.ini .APLI BRX-translations.trans03.ini .APLI BRX-translations.trans03.ini .APLI BRX-translations.trans03.ini	" co	nd then, a message appears, OK It succeeded. Press any key to ntinue" nen press the "Enter" key.
bă Pile(3) copied OK ît succeede Press any key te continue		If a message appear except "OK It succeeded. Press any key to continue", you should restart the PC and implement program update from "EPC the latest Program Update- 1" again.

7.EPC the Latest Program Update has been completed

HI C EAAL					× 🗊 🙃
- Institution of the second	Nete -	Sa	Турн	Date Modified	Date Picto
The and Fulder Lake (*)	©PPI 12 Add constant ⊘HASP3ceSetation		Pie Polder HS-DOS Butch File Application	10(27)2009 6-40 PP 10(27)2009 6-28 PM 10(27)2009 6-28 PM	L
Differ Planes					
Details (*)					

* EPC the latest Program Update has been completed. Please leftclick the "X " button to close the window.



After EPC the Latest Program Update has been completed, please check the EPC version by starting the "TOYOTA EPC SYSTEM". When the EPC version on the "TOYOTA EPC SYSTEM" corresponds to the version which has been announced by TMC, program renewal has been implemented correctly.


2-2-6. recovery

1. Procedure of Program Recovery



Please end "TOYOTA EPC SYSTEM" if it is activating to recover the program.

- (1) Procedure of Program Recovery
 - 1. Program Recovery-1



* Left-double-click the "My Computer" on the desktop

2. Program Recovery-2



*Left-double-click " the destination drive where EPC has been installed "

example

When the destination drive where EPC has been installed " is "C Drive", please left-double-click "C Drive" 3. Program Recovery-3



5. Program Recovery-5

APLI				28	
e Edit View Pavorites To	ols Help				2
Juil . O 3 1	🤇 Search 🍋 Polders 💷 -				
C.(INCEPCHIARLI				3 E	2
		See	Type	Date Modified	10
File and Folder Tasks	Translations 🔁		File Folder	10/27/2009 6:40 PM	
and Remains that He	an Aci, Receivery Lot.	238	MS-DOO Batch File	10/27/2009 6-28 FM	
Contraction of the second s	Sept_db2.dl	6443	Application Extension	10/27/2009 6:28 PM	
🙀 How that No.	Sec. and	6842	Application Extension	10/27/2009-6-28 PM	
Copy this file	Bepc_loca.dl	72 KB	Application Extension	10/27/2009 6:28 PM	
Publicit this file to the West	Teps_milds.eve	40 KB	Appleisten	10/27/2005 6:28 PM	
() E-mul this file	Dept.prn.exe	192 80	Application	10/27/2009 6:28 PM	
in Personal Para	Bepc_src0.dl	140.80	Application Extension	10/27/2009 6:28 PM	
Y Deats this file	Bepc_rcl.dl	84 #B	Application Extension	10/27/2009 6-28 PM	
X Deeps Dis rat	Sept_src2.dl	68 KB	Application Extension	10/27/2009 6:28 PM	
	Bec.pc3.dl	129.40	Application Extension	10/27/2009-6-28 PM	
Other Places	Bepc_arit4.dl	5248	Application Extension	10/27/2009 6-28 PM	
CONFI FRACES	Bepc_prd5.dk	4445	Application Extension	10/27/2009 6-28 FM	
THODROWS	Sepc_arcs.dl	04 KB	Application Extension	10/27/2005 6:28 PM	
A My Documents	Sepc_97.7.4	7648	Application Extension	10/27/2009 6:28 PM	
Thered Documents	Sept_ortf.dl	129.88	Application Extension	10/27/2009 6:28 PM	
	Sept_sche.dl	68 #B	Application Extension	10/27/2009 6:28 PM	
Hy Conputer	EPCENV.BAK	348	BAK File	11/9/2009 3:21 AM	
My Nettoisk Flaire	3 EPCENV.34	340	Configuration Settings	11/9/2009 3:21 AM	
and the second second	- @epcsetup.ev#	1,072 KB	Application	10/27/2009 6:28 PH	
Detaily	September and the second secon	18B	MANDPEST File	10/27/2009 6:28 PM	
Details	Depctickt.dl	720 KB	Application Extension	10/27/2009 6-28 PM	
	ana.ang	140	PNG Image	10/27/2009-6-28 PM	2
	6				8

* Left-double-click the "Apli Recovery.bat"

6. Program Recovery-6

C:WRDOWSUSystem32kcmd.exe .xAPLI_BAK\translations\dencata_83.ts .wAPLI_BAK\translations\dencata_84.ts .wAPLI_BAK\translations\dencata_84.ini .wAPLI_BAK\translations\dencata_84.qn .wAPLI_BAK\translations\dencata_84.qn .wAPLI_BAK\translations\dencata_84.qn .wAPLI_BAK\translations\dencata_85.ini .wAPLI_BAK\translations\dencata_85.ini .wAPLI_BAK\translations\dencata_95.ini .wAPLI_BAK\translations\dencata_95.ini	 * Wait for a while. A message appears, "OK It succeeded. Press any key to continue" Please press the "Enter" key.
68 File(s) copied OK It succeeded Press any key to continue	If a message appear except "OK It succeeded. Press any key to continue", you should restart the PC and implement program recovery again.

7. Program recovery has been completed

DARL				E (5	8	*D 1 1
ie Edit View Pavorites Took	i 160					* Program recovery has bee
3 ml . O 1 /	Search 🎦 Polders 💷+				1	completed.Please Left-click
the CINTREPORTARIA				1	20	1
and the state of the state of the state of the	Natie -	See	Type	Date Modified	10	- "X" button.
File and Folder Lasks	Contranslations		File Folder	10/27/2009 6:40 PM		
B Renative that file	The Ack Recovery Lot	28B	MS-DOS Batch File	10/27/2009 6-28 FM		
No-o the file	Sec.do.d	64.83	Application Extension	10/27/2009-6:28 PM		
	Bex did	68.42	Application Extension	10/27/2009-6-28 PM		
Capy the file	Sepc_loca.dl	72 KB	Application Extension	10/27/2009 6:28 PM		
Publish this file to the Well.	epc_mkdu.eve	40 KB	Appleation	10/27/2009 6:28 PM		
Count the file	apc_pro.exe	192 80	Application	10/27/2009 6:28 PM		
the investment file	Sepc_src0.dl	140.88	Application Extension	10/27/2009 6:28 PM		
X Delete this file	Bepc_incluit	04 #B	Application Extension	10/27/2009 6-28 PM		
× Deete Dane	Bepc_src2.4ll	68 KB	Application Extension	10/27/2009-6:28 PM		
	Berc.uchd	128.40	Application Extension	10/27/2009-6:28 PM		
Other Places	Bepc_arc4.dl	52 48	Application Extension	10/27/2009 6-28 PM		
estent eddrar	Gillabc Nrtzrug	44.65	Application Extension	10/27/2009 6:28 PM		
THODACWS	Sepc_src6.dl	04 KB	Application Extension	10/27/2005 6:28 PM		
Atty Documents	Sept_31(7.08	7648	Application Extension	10/27/2009-6:28 PM		
Thered Documents	Sepc_ot#.dl	129 #8	Application Extension	10/27/2009 6:28 PM		
N Ply Conjorter	Sept_yohe.dl	68 #B	Application Extension	10/27/2009 6:28 PM	100	
	EPCENV.BAK	348	BAK File	11/9/2009 3:21 AM		
My Nettoick Flaces	Gencenv.au	340	Configuration Settings	11/9/2009 3:21 AM		
	@epcsetup.exie	1,072 KB	Application	10/27/2009 6:28 PH		
1.1	Bepcsetup.exe.manifest	1 #B	MANDPEST File	10/27/2009 6:28 PM		
Detain (*)	Depcticalit dl	720 KB	Application Extension	10/27/2008 6-28 PM		
	3 no.ong	183	PNG Image	10/27/2009 6:28 PM	2	
	é				ST/	



After program recovery has been completed, please check the EPC version by starting "TOYOTA EPC SYSTEM". When program recovery has been implemented correctly, the end of the version number becomes " 9 "

version before recovery : V1.0 L50 R060 [example] version after recovery : V1.0 L50 R069

3. Setup Procedure of Server / Client Type

Setup at Server PC



When performing program update...



When performing program recovery...

EPC Program Recovery (Refer to 3-2-7 : p.69)

Setup at Client PC



** In client, setting of the "LEXUS Dealer Check" cannot be performed. If it is set at the server, searching the LEXUS catalog from the client becomes possible.

When performing program update...

EPC Program Renewal

(Refer to 3-3-6 : p.89)

When performing program recovery...

EPC Program Recovery (Refer to 3-3-7 : p.90)

3-2-1.EPC Program Install

(1)Opening Windows and inserting a A1DVD to the DVD drive.



- * Turn on your computer to open a Windows.
- * After the Windows is start up, insert the A1DVD to the DVD-ROM drive.
- * Right-click the "My Computer" on the desktop and left-click the "Explore".

(2)Running the install system from a A1DVD.



- * Left-click the drive where you have set the A1DVD.
- * Double-click the "setup.exe".

(3)Starting the Installation



- * To execute the TOYOTA EPC Install, left-click the "Next" button.
- * To cancel the installation, left-click the "Cancel" button.
- * A message for asking if you cancel the installation or not will appear again. Click the "OK" button to cancel the installation or click the "Cancel" to continue.

(4)Selecting a drive for the installation.



- * Select the drive where you want to install the TOYOTA EPC, and left-click the "Next" button.
- * To cancel the installation, left-click the "Cancel" button.
- * If installing for the first time, go to (6) [Selecting a system configuration.

(5)Checking the Install Configuration [Some install configurations may have the following A) or B) case.]

A)In case that the EPC is already installed,



- * To install it again, left-click the "Next" button to transit to (7) [System Installation].
- ** Even if a new system is already installed, another installation will maintain the existing setup information.
- * To go back to the previous screen(4) [Selecting a drive for the installation], leftclick the "Back" button.
- * To cancel the installation, left-click the "Cancel" button.

B)In case that the disk space isn't enough,

TOYOTA ELECTRONIC PARTS CATALOG INSTALL
(installation carrying out the minimum 10/240MB is required) in order to stop installation, please click [cancellation]
Cancel

* The EPC installation needs the disk space of 10 MB. To change the drive for the installation, left-

click the "Back" button to go back to the previous screen (4) [Selecting a drive for the installation].

* To cancel the installation, left-click the "Cancel" button.

(6)Selecting a system configuration



- * Select a system configuration ("Server"), and left-click the "Next" button.
- * To cancel the installation, left-click the "Cancel" button.

(7)System Installation



* Wait for a while until the installation from the CD has been completed.

(8)Copying a setup file



- * If there isn't the copy of the setup file, select the "No" and left-click the "Next" button to transit to (11) [Setting a background image].
- * If there is the setup file, select the "Yes" and left-click the "Next" button to transit to (9) [Selecting the drive where the setup file is inserted].

See (p.137) for the setup file copy

(9)Selecting the drive where the setup file is inserted.



- * Insert a floppy with the setup file to the floppy drive, select the drive where you inserted the floppy, and then left-click the "Next" button.
- * To cancel the copy of the setup file, left-click the "Back" button to go back to the previous screen (8) [Copying a setup file].
- ** In the case that a correct floppy drive or a floppy with a correct setup file isn't setup, an error message of "An applicable file is not found." will appear. You should setup it again correctly.

(10)Copying a file



* Wait for a while until the setup file has been copied from the floppy.

(11)Setting a background image



- * If you setup the default background image to this EPC screen, select the "No" and left-click the "Next" button to transit to (13) [Completing the installation].
- * If you want to setup the background image of your own choice to this EPC screen, select the "Yes" and left-click the "Next" button to transit to (12) [Selecting a background].

What is background image?

You can display the image you prefer as background of the menu screen.

(12)Selecting a background image



- * To setup the background image to the Main Menu, left-click the "browse" button and select a file, then left-click the "Next" button.
- * To setup the background image to other than the Main Menu, left-click the "browse" button and select a file, then left-click the "Next" button.
- ** The file types of JPEG, BMP,and PNG can be selected as a background image.
- * To go back to the previous screen (11) [Setting a background image], left-click the "Back" button.

(13)Completing the installation



- * As the EPC installation is completed, left-click the "Finish" button.
- ** When the installation is complete, extract the A1DVD from the DVD-ROM drive.

When having used the 2007 version of this New EPC, please kindly follow the following procedure of (14) and (15). When newly using the 2008 version of this New EPC, you do not need to follow the procedure of (14) and (15).



(14)Deleting number information of the old frames

* Right-click the "My Computer" on the desktop and left-click the "Explore".



	nth 🜔 Fallers 🖓 🖉	× 9 🗉		
iddees W Conouter	K Name	toe	Total Size	- 0-
Potters :	Files Stored as This Core		Cold See	Free Spare Consumpt
E C Wy Donametry				
- He shared and a	Pandbauevis	Pile Polider		
IN	Admethese's Documents	Fill Fuller		
See Land Des. (D.)	Hard Disk Drives			
N	Earlined Data (C)	Local Delt.	5.00 (A)	2.15.00
= 🗶 oktyles (6.)	Geland Dis (D)	Location	9, 10 (2)	5.04 (2)
III (Del) Delver (m.)	Contraction of the second			
IE Z DAIMEL (V)	Devices with Removable	Storage		
IN 2 DRIVERS (D)	ATS Please (A.)	21s but Picpoy Dell		
- Control Faced	(Jupito Drive (H))	CD Drive		
IF 🔐 Shand Conuments	Network Drives			
R C Advanto-stor's Decements				
all Result day.	S00029)	fathout Drive	15.4 (2)	4.78.08
	ZDADER (S.)	Disconcented Network Drive Network Drive	1000	4.79-08
	CALVERT (A.)	Network Drive	18.4 (8)	4.75.08
	2000 (MAL (2))	National Drive	18.4 (2)	4.75.08
	The second second			
	+1			
	111			

* Left-click the drive where the data is set up.



* Left-click the "TMCEPCW3" folder.

The Life Termine Termine Tools	100		
0 tat + () + (1) Seet		K 10 TT-	
Address D 17900PCWD			- 0
viters X		Sim Type	Date Multired
Desing Desing	Carolate Car	File Folds File Folds File Folds File Folds File Folds File Folds File Folds File Folds File Folds File Folds	1117412007 % 0.189 111742007 % 0.999 111742007 % 0.999

* Left-click the "epcdata" folder.



* Left-click the "FL" folder.

(15) Deleting the folders OV1-OV5



- * If the folders "OV1"-"OV5" exist, delete them with Shift+Delete.
- ** If the "OV" folder already exists, do not delete this folder.

(16)Starting the TOYOTA EPC SYSTEM



*Insert the A1DVD to the DVD drive.

* Double-click the "TOYOTA EPC SYSTEM" on the desktop to start the TOYOTA EPC SYSTEM.

*If using the current EPC group setup file...

Setup procedure

1.Copy the Group Setup Files to the Floppy Disk. (Group Setup Files: <u>TMCMSTW2¥GCGRPMEI.D</u> and <u>TMCMSTW2¥GCGRPPNC.D</u>) 2.See (8) [Copying a setup file] on (p.44).

3-2-2.EPC Data Setup

(1) Data environment setup

* Press Setup Menu.

Click Data Configuration button.



Reference: Description of the buttons in Setup Menu screen

* Data Configuration	: Setups Data Operation(DVD/Hard Disk/Server). Run this setup first after the EPC system is installed.
* Data Setup	: Setups the data with the contents created on the [Data Configuration] screen. This setup must be run whenever the data is update.
* Area/Language Setup	: Setups Data Language and Screen Language. Select an Area when the data of multiple Areas are setup.
* Group Setup	Catalog Codes and Part Name Codes which are often searched should be registered here so that you can search the data by Group Code.
* Screen File Setup	: Use when changing a displayed title on the screen.
* Setup File Copy	The setup Environment can be copied on other computers It will be helpful to operate multiple computers under the same environment.
* Locally Supplied Parts Setup	: Setup the data here when searching for Locally Supplied Parts.
* Price File Setup	: Setup the data here when searching Price File.
* Another Interface Application Setup	: Use when operating another system using the search results on EPC system.
* LEXUS Dealer Check	: Lexus Dealer must enter a given password so that you can search Lexus catalog.
** Clicking the "Menu" button ends th	e Setup Menu and goes back to the Main Menu.

(2) Entering Sales Area Code

Area	Fee He	Dete	1	The Bounts of Copy	Overgrat	
Factor	4.1		-			•
General	42		븰			•
HEA, Canada Japas	81	1				9
Cable	14		-			•
	10		•			•
	84		-			•
-	85			*		
A	Fer Bu	Dete			Output	
Overness Japan	P3	-	리			•
Sabar	12		*			•
	11		-			•
	74		21			1
	78		-			긬
	F4		-	-		4
and the second division of the second divisio	11	1	킈			
Trans Resal Cash	Inc Ro	Date		The Source of Copy	- Data part	
and the state of the	#1					
	#2		-			
10	RI .					
Pror.	Local file					
Pitter.	Frite File		1		-11	

- * In order to search substitution part number/procurement part number corresponding to the region, enter the 5-digit Sales Area Code.
- * Sales Area Code will be described separately.
- * The ticked product numbers will not be searched.
 - If "Procr" is ticked, the procurement part number will not be displayed.
 - If "Subs" is ticked, the substitution part number will not be displayed.

(3) To setup the operation for EPC (Catalog) data



- * Select the Area you want to setup. Select the type of DVD (Area) you want to set.
- * Setup the EPC data here. Select the Area you want to setup, and setup the method for operating and the recorded place of the data for each Rec#.
- * Setup the method of your operation. Select a CD-ROM/HardDisk /Server from a pull-down list box.
- ** When installed with "Server", you can select only "HardDisk".

Europe General IIIIA, Canada Japan	A1 42 91	Barithink	1		
HIA, Canada	81	-	1	N.	
		1			٠
(abet)	11		- P-1		- 21
		-	• 11		-lefter
	83		• G.c		•
	24		N.		
	85				-
	direct of				
	1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	the second s	ADItenty		
(Area	Ber Bo	Data	The Bourne of Com-	r Ovtget	
Oversess	P3				٠
2apan	12	1	2	2	telle helte helte helte
	11		1		•
	74	-	*	2	٠
	72		•	-	٠
	74			-	٠
	11		-		٠
		7			
and the second sec					
Sales Bess Lode	Sec No	Date	The Bruces of City	T Output	
	81	-			-
29995	80		2	-	-
184	#1		-	2	-
Pror.	Local File		2		
17 Sales	Frice File			1	

- * Select the drive where the catalogue data is set.

Area	Day Ho	Dute.	The Bussie of Cop-	V Det set	
Barnpe .	41	Bac (D-Left			-
General	4.2	-		•	
Hild; Canada] Japan	81		2	X Ct	
Catao -	81				
	83		-	-	
	24	-	-		
Concession of the local division of the loca	91				-1
				1	
		and the owner water of the owner		21	
Ante	Rec Br	Date	The fourne of Copy	p Output	
Oversear	Fi	1	+	-	•
Japan	12		-	*	
	13		-	*	•
	74		•1	2	•
	11		•		
	71		30	2	
	17		-		teltelteltelte te
- Sales Read Code	Sec Bo	Deta	The Bourne of Con	PF Output	
0000	E1		-		-
	81			2	utetetete
18th	#1	1	2	2	٠
E Pesta	Local File		-		
C'ANN .	frice file		2	1	-
					_

 \square

- * In the case that the Hard Disk is set, select a drive where the data is copied.
- ** In case of the Server, you can't set the drive.

(4) To setup the operation for EPC (FrameNo) data

Anne	Fee Be	Date.		The Source of Copy	Overgrant	_
Europe	A1	Barith Len			D4.	
General	42	Datistran.				- total
HIA, Canada	11					
Zapan	11					
	10					
	14					
	15		-	1		-
	115	and the second se	-			-
A++	Ber Bu	Data		The Bourne of Copy	Output	
Overses	13	BAC UP 1.6 R		1i	61- 01	
Japan	72		*		2.5	
	11		•) <u> </u>	R+	
	74			2	04	
	75				Fi G: #1 X1	
	F4				01	
	17					
Sales Rest Cade	Sec No.	Date		The Source of Copy	Ti Zi Sungun	
222233	#1		-		•	
	#2 ·				•11	
Hate	81				1	
C Pres	Local File				•	
Pitates	Frice File				•	
				-		
	Please	choice the appropriate	FPC CI	(is) you want to use		-
A REAL PROPERTY AND					and some site to be seen in	_
Marta				Burtania a		

- * Perform the same operation about FrameNo DVD
- * As the number becomes bigger, the frame information will be newer. (F1 is the oldest DVD.)

(5) To setup the operation for JPIO, Local File, and Price File



- * Perform the same operation about JPIO, Local File and Price File as well.
- ** As for Local File and Price File, only operation method (HardDisk only) and the Output place can be selected.
 The actual data should be set on the [Locally Supplied Parts Setup] and [Price File Setup] screen.
- ·Setup J-PIO to M1
- See (p.96) for Locally Supplied Parts Setup
- See (p.94) for Price File Setup

	Fee Bu	Date.		The Bounce of Copy	Overgrad	1
Europe	41	Parid Lak			84.	
General	AT		•			
HIA, Canada	81	-	•			
Zapan	84					-
	83	-	•			
	84					
	85	-			1	
A++	Ber Ito	Deta		The Bourde of Copy	Output	
Over seas	<u>r1</u>	BACULTE	-		1 P±	-
Colored Colored	12		•			
	73 74		•			
					11	
			-			
	75		-			-
			1			1.1.1
Salara Brasilinda	75 74	2ata	1	The Sences of Copy	Charge A	
Nation Rest Code	FS F4 F7 Sec Re R1	Date Partifitak	1	The Sences of Copy	Osagua 2011	
89995	FS F4 F1 F1 F1 F1 F1 F2 F2		100	The Brucce of Story (7)		
Hale	FS F4 F1 Bec Re E1 E2 E1	Rec (D) Lett	100	The Brucce of Story (7)		
89995	FS F4 F1 F1 F1 F1 F1 F2 F2		1	The Brucce of Story (7)		

ŢĹ

* After you set the data environment, click the "Exec" button.



- * Click the "OK" button.
- * Click the "Menu" button to return the "Setup Menu".

(6) Data Setup





- * The setup Information on the setup Area is displayed.
- * Select an Area.
- * Select a Rec# of the data .
- You can select multiple Rec#s.
- ** If an Area or a Rec# you want to setup isn't listed, setup the environment on the [Data Configuration] screen.





- * After you select the Rec#, click the "Exec" button.DVD confirmation message will be displayed.Set the corresponding DVD.
- ** When the setup is complete, the date of the data will be updated.
- ** When setting up the data for several Areas, change the Area and select the Rec#.



- * When the setup is complete, dialog is displayed. And then click the "OK" button.
- ** If you want to setup other Area, repeat the same operation after changing Area.After all setup is complete, click the "Menu" button to go to the "SETUP MENU".

3-2-3.Area / Language Setup

The Area you want to search on the EPC system and the Screen Language can be selected.

-Area	: The Area which has setup on the [Data Setup] screen can be selected.
	The Area which is selected here is searched.
-Data Language	: When the data such as Part Names, Illustration Name etc, is provided by each
	language, the Language Data which is selected here is displayed.
-Screen Languag	e : The contents on the screen are written in the Language which is selected here.

Please select "Area/Language Setup" of "SETUP MENU".



3-2-4.LEXUS Dealer Check

TOYDTA ELECTIONS PARTS GATALOS SYSTEM VEN LSB PRIM Same Mend	
Table Configuration	Locally Supplied Danis Solve
	and the second se
Entra Satur	Pite 1 in Setue
and the second s	and the second s
Areat any any Setur	Animet Meetlac: Repleation Silvar
	*
	11805 Dealer Direct
Gray Teles	
Second Bit Selan	You are not regarded as a Learn dealer. You cannot not Learn couldry.
	You cannot may be an catalogs.
Security Copy	
Select one term to be set up by siding	scroll bar and press the erder key
Martin Balancia Database Analysis Description	Alterna Alterna Alterna Alterna Alterna
	7
	Ļ
\sim	
TOYOTA ELECTRONIC PARTE CATALOG SYSTEM V	1 II LOU HURD [] CHIEF Dealer Clinick]
Function Back friet line	And 22
Personal	
Enter the LENUS dealer password given	for this set of CDs and press F8 key
Chie Menu	Line Line

- * In order to use the LEXUS catalog, you need the LEXUS password.
- * Click the "LEXUS Dealer Check" button.

- * Enter a LEXUS Password and click the "Exec" button.
 - The only right password allows you to use this LEXUS Catalog.

To clear the displayed contents ;

unction Back Print	FROME PARTE CATALOG SYSTEM VLB LIN FURD DEDDE INUM # Jing	
	Passavet	
Enter	the LEXUS dealer password given for this set of CDs and pre	rists Fill keey

Clear

* Click the "Clear" button to delete the displayed data.

3-2-5. Prior Check (sharing folders)

In order to allow the client to read the data in the server, perform drive sharing at the server side according to the following procedure:

Drive to perform sharing	\rightarrow	Drive of the server in which the program is installed	
	\rightarrow	Drive of the server in which the data is set up	

Sharing the drive of the server where the program is installed (When the EPC System Install Drive is in the "C" drive.)

(1) Activate the Explorer and display the property of the "C" drive



(3) Setting the access permit



- * Tick "Full Control" in the access permit of "Everyone" user, and left-click the "OK" button.
- ** If the above setting is already applied, leftclick the "OK" button to return to the property screen.

* Close the property screen by left-clicking the "OK" button.

Sharing the driver of the server where the data are set up (When the EPC Data Setup Drive is in the "D" drive.)

(1) Activate the Explorer and display the property of the "D" drive



(2) Share the "D" drive.



- * Select "Share this folder" with left-click
- * Left-click the "Permissions" button to perform the setting of the access permit.

(3) Setting of the access permit



- * Tick "Full Control" in the access permit of "Everyone" user, and left-click the "OK" button.
- ** If the above setting is already applied, leftclick the "OK" button to return to the property screen.
- * Close the property screen by left-clicking the "OK" button.

3-2-6. Procedure of Program Renewal by A1DVD

1. Program Renewal Message

The message appears on the screen if the new program exist in it when setting up A1DVD. In this case, please implement renewing the latest program by referring to "Program renewal by A1DVD"

(1) Checking the program renewal message

1. EPC Data Setup



* Setup EPC data according to the normal procedure.

2. The EPC installation is completed



* When the setup is completed, a dialog is displayed. Please click the "OK" button.

3. Checking the program renewal message



Check the new version, and then Left-click on the "OK" button.



The program is not renewed automatically just by pressing the "OK" button. Please implement renewing the program by referring to "Program renewal by A1DVD".

2 .Program Renewal by A1DVD



Please end "TOYOTA EPC SYSTEM" if it is activating to you renew the program by A1DVD.

(1)EPC the Latest (EPC) Program Update

1.EPC the Latest Program Update-1



2.EPC the Latest Program Update-2



* Left-double-click " DVD-ROM Drive"

3.EPC the Latest Program Update-3



* Left-double-click the "APLI" folder

4.EPC the Latest Program Update-4

PAGE 1				L 🗆 🔛
lie Edt View Pavortes To	ols Help			10
3 tok + () 3 3	Search 🕑 Pokders 🛄+	ſ		_
ASHE CENNI				
File and Folder Tasks 7 Tasks the file Toron the file Copy the	New All Converse Internet Setup Aver	Son Type Pile Pode 418 MS-505 Becch File 8,643 KB Application	Date Hodfeet 10(27)2000 6-40 PH 10(27)2000 6-30 PH 10(27)2000 6-30 PH	Date Pictu
Other Places				
Details (3	2			
		-	-	2

* Left-double-click "Apli_Copy.bat"

5.EPC the Latest Program Update-5



* A message appears,"Input the destination drive where EPC has been installed"

Input the destination drive where EPC has been installed, then press "Enter" key.

If you inputted the drive where EPC is not installed, input it again correctly. Then press the "Enter" key. 6.EPC the Latest Program Update-6



7.EPC the Latest Program Update has been completed

HI C EAAL					× 🗊 🙃
- Institution of the second	Nete -	Sa	Турн	Date Modified	Date Picto
The and Fulder Lake (*)	GPOI TERESCONTRAC € HASPGerSetup.eve		File Folder HS-DCS Bach File Application	10(27)2009 6-40 PM 10(27)2009 6-28 PM 10(27)2009 6-28 PM	
Differ Planes					
Details (*)					

* EPC the latest Program Update has been completed. Please left-click the "X " button to close the window.



After EPC the Latest Program Update has been completed, please check the EPC version by starting the "TOYOTA EPC SYSTEM". When the EPC version on the "TOYOTA EPC SYSTEM" corresponds to the version which has been announced by TMC, program renewal has been implemented correctly.



- 3-2-7. recovery
 - 1. Procedure of Program Recovery



Please end "TOYOTA EPC SYSTEM" if it is activating to recover the program.

- (1) Procedure of Program Recovery
 - 1. Program Recovery-1



* Left-double-click the "My Computer" on the desktop

2. Program Recovery-2



*Left-double-click " the destination drive where EPC has been installed "

example

When the destination drive where EPC has been installed " is "C Drive", please left-double-click "C Drive"
3. Program Recovery-3



5. Program Recovery-5

Details

Ŧ

APLT				2 A	
e Edit Vew Pavorites Tools	Help			Sectore .	-
3 wa . 0 1 p	Search 🐑 Polders 💷+				
CINKEPOWSIARU				3 B	2
		See	Type	Date Modified	10
File and Folder Looks	Contranslations		File Folder	10/27/2009 6:40 PM	
all Remains that Her	And Apl Receivery Lot	23.8	MS-DOO Batch Pile	10/27/2009 6-28 FM	
Contraction of the second s	Sept_db2.dl	6443	Application Extension	10/27/2009 6:28 PM	
All the Martin Mar	Second	6842	Application Extension	10/27/2009-6-28 PM	
Copy this file	Sept_loca.dl	72 KB	Application Extension	10/27/2009 6:28 PM	
Publish this file to the Well	Enge_nikids.ese	40 KB	Appleisten	10/27/2005 6:28 PM	
C E-mail this file	Enc.pro.exe	192 80	Application	10/27/2009 6:28 PM	
the President Part	Sept_arc0.dl	140.80	Application Extension	10/27/2009 6:28 PM	
X Deate this file	Bept_incl.dl	84 #B	Application Extension	10/27/2009 6-28 PM	
X Deece Distrie	Bept_pr(2.dl	68 KB	Application Extension	10/27/2009 6:28 PM	
1	Sec. wa.d	129.40	Application Extension	10/27/2009-6-28 PM	
Other Places	Bept_arc4.dl	5248	Application Extension	10/27/2009 6-28 PM	
Contraction of the second s	Sept_arc5.dl	4445	Application Extension	10/27/2009 6:28 PM	
THODACWS	Sept_arch.dl	04 KB	Application Extension	10/27/2005 6:28 PM	
A My Documents	Sept_917.4	7648	Application Extension	10/27/2009-6:28 PM	
Thered Documents	Sept_ott.dl	129.80	Application Extension	10/27/2009 6:28 PM	
1 Py Coloritor	Sept_yshe.dl	68 #B	Application Extension	10/27/2009 6:28 PM	10
	EPCENV.BAK		BAK File	11/9/2009 3:21 AM	
Mr Nethnak Places	G-EPCENN.INE	340	Configuration Settings	11/9/2009 3:21 AM	
	generatup.exe	1,072 #8	Application	10/27/2009 6-28 PM	
Details (a)	Sepcietup.exe.manfeat		MAIdPEST File	10/27/2009 6:28 FM	
Metalle 120	Septicit d		Application Extension	10/27/2009 6-28 PM	
	Distance	140	PNG Image	10/27/2009-6-29 PM	
	e				5

* Left-double-click the "Apli Recovery.bat" 6. Program Recovery-6

C.WINDOWS/System32kcmd.exe	 * Wait for a while. A message appears, "OK It succeeded. Press any key to continue" Please press the "Enter" key. If a message appear except "OK It succeeded. Press any key to continue", you should restart the PC and implement program recovery again.
----------------------------	---

7. Program recovery has been completed

APLI				EÆ	83	
ie Edit View Pavorites Tools	Help					* Program recovery has b
3 tod + 😳 🦸 🔎	Search 🍋 Polders 💷+					completed.Please Left-cl
there C. (INCEPCHOLARLI				× 🗈	Ga	1
and the state of the state of the state	Nane -	See	Type	Date Modified	100	– "X" button.
File and Folder Looks	Contranslations		File Folder	10/27/2009 6:40 PM		
10 Remaine this file	and Apl Recovery lost	218	MS-DOS Batch File	10/27/2009 6-28 PM		
	Sept_diQ.dl	64435	Application Extension	10/27/2009-6-28 PM		
🙀 Hore the Ne	Bex.did	68.42	Application Extension	10/27/2009-6-28 PM		
Copy this file	Sept aca d	72 KB	Application Extension	10/27/2009 6:28 PM		
Publish this file to the Wett	Teps_mids.eve	40 KB	Appleisten	10/27/2009 6:28 PM		
C E-mail this file	Dept.pm.eve	192 80	Application	10/27/2009 6:28 PM		
the Person file	Sept_arc0.dl	140.88	Application Extension	10/27/2009 6:28 PM		
	Depr. arcl.dl	84 #B	Application Extension	10/27/2009 6-28 PM		
X Delete this file	Bepc_src2.dll	68 KB	Application Extension	10/27/2009-6-28 PM		
	Bec.ro.d	128 48	Application Extension	10/27/2009-6:28 PM		
Other Places	filepc_arc4.dt	52.48	Application Extension	10/27/2009 6:29 PM		
uther maters	Sept. prc5.dt	4445	Application Extension	10/27/2009 6:28 FM		
THOPEWS	Sept_srch.dl	0485	Application Extension	10/27/2005 6:28 PM		
A My Documents	5)epc_src7.d8	7648	Application Extension	10/27/2009-6-28 PM		
and the second sec	Sept_orti.dl	129 83	Application Extension	10/27/2009 6:28 PM		
California Started Documents	Sept. yohn.dl	68 #B	Application Extension	10/27/2009 6:28 PM	1.00	
Hy Conputer	depceny.bar	348	BAK File	11/9/2009 3:21 AM		
My Nethelak Flaces	GEPCENV. BIL	340	Configuration Settings	11/9/2009 3-21 AM		
Contraction of the second second	@epceetup.eve	1.072 #8	Application	10/27/2009 6:28 PH		
1000	Deposetup.ene.manifest	188	MANDPEST File	10/27/2009 6:28 FM		
Detaile a	Depctickt d	720 ¥B	Application Extension	10/27/2009 6-28 PM		
	Incong	1 #25	PMG Image	10/27/2009-6-28 PM	10	
	6				5	



After program recovery has been completed, please check the EPC version by starting "TOYOTA EPC SYSTEM". When program recovery has been implemented correctly, the end of the version number becomes " 9 "

version before recovery : V1.0 L50 R060 [example] version after recovery : V1.0 L50 R069

3-3-1. Prior Check (drive allocation)

In order to read the data in the server from the client, perform the network drive allocation for the shared drive according to the following procedure.

Client drive that performs the allocation	\rightarrow arbitrary (drive in which the program	
	of the server side is installed)	
	\rightarrow arbitrary (drive in which you have set	
	up the data of the server side)	
L		

Setup at Client PC

Allocation of the EPC program

(1) Activate the Explorer



* Right-click the "My Computer" on the desktop and left-click the "Explore".

(2)Set the connection for the drive shared by the server.



(3)Enter the machine name and shared folder name in the pass column.



Data allocation

*The procedure of allocation is same as

3-3-2.EPC Program Install

(1)Opening Windows and inserting a A1DVD to the DVD drive.



- * Turn on your computer to open a Windows.
- * After the Windows is start up, insert the A1DVD to the DVD-ROM drive.
- * Right-click the "My Computer" on the desktop and left-click the "Explore".

(2)Running the install system from a A1DVD.



- * Left-click the drive where you have set the A1DVD.
- * Double-click the "setup.exe".

(3)Starting the Installation



- * To execute the TOYOTA EPC Install, left-click the "Next" button.
- * To cancel the installation, left-click the "Cancel" button.
- * A message for asking if you cancel the installation or not will appear again. Click the "OK" button to cancel the installation or click the "Cancel" to continue.

(4)Selecting a drive for the installation.



- * Select the drive where you want to install the TOYOTA EPC, and left-click the "Next" button.
- * To cancel the installation, left-click the "Cancel" button.
- * If installing for the first time, go to (6) [Selecting a system configuration].

(5)Checking the Install Configuration [Some install configurations may have the following A) or B) case.]

A)In case that the EPC is already installed,



- * To install it again, left-click the "Next" button to transit to (7) [System Installation].
- ** Even if a new system is already installed, another installation will maintain the existing setup information.
- * To go back to the previous screen(4) [Selecting a drive for the installation], leftclick the "Back" button.
- * To cancel the installation, left-click the "Cancel" button.

B)In case that the disk space isn't enough,

TOYOTA ELECTRONIC PARTS CATALOG INSTALL
(installation carrying out the minimum 10/240MB is required) in order to stop installation, please click [cancellation]
Cancel

* The EPC installation needs the disk space of 10 MB. To change the drive for the installation, left-

click the "Back" button to go back to the previous screen (4) [Selecting a drive for the installation].

* To cancel the installation, left-click the "Cancel" button.

(6)Selecting a system configuration



- * Select a system configuration ("Client"), and left-click the "Next" button.
- * To cancel the installation, left-click the "Cancel" button.
- * Select the drive for the program of the server side that is allocated on (p.72) for Prior Check (drive allocation).

(7)System Installation



* Wait for a while until the installation from the DVD has been completed.

(8)Copying a setup file



- * If there isn't the copy of the setup file, select the "No" and left-click the "Next" button to transit to (11) [Setting a background image].
- * If there is the setup file, select the "Yes" and left-click the "Next" button to transit to (9) [Selecting the drive where the setup file is inserted].

See (p.137) for the setup file copy

(9)Selecting the drive where the setup file is inserted.



- * Insert a floppy with the setup file to the floppy drive, select the drive where you inserted the floppy, and then left-click the "Next" button.
- * To cancel the copy of the setup file, left-click the "Back" button to go back to the previous screen (8) [Copying a setup file].
- ** In the case that a correct floppy drive or a floppy with a correct setup file isn't setup, an error message of "An applicable file is not found." will appear. You should setup it again correctly.

(10)Copying a file



* Wait for a while until the setup file has been copied from the floppy.

(11)Setting a background image



- * If you setup the default background image to this EPC screen, select the "No" and left-click the "Next" button to transit to (13) [Completing the installation].
- * If you wan t to setup the background image of your own choice to this EPC screen, select the "Yes" and left-click the "Next" button to transit to (12) [Selecting a background].

What is background image?

You can display the image you prefer as background of the menu screen.

(12)Selecting a background image



- * To setup the background image to the Main Menu, left-click the "browse" button and select a file, then left-click the "Next" button.
- * To setup the background image to other than the Main Menu, left-click the "browse" button and select a file, then left-click the "Next" button.
- ** The file types of JPEG, BMP,and PNG can be selected as a background image.
- * To go back to the previous screen (11) [Setting a background image], left-click the "Back" button.

(13)Completing the installation



* As the EPC installation is completed, left-click the "Finish" button.

(14)Starting the TOYOTA EPC SYSTEM



*Insert the A1DVD to the DVD drive.

* Double-click the "TOYOTA EPC SYSTEM" on the desktop to start the TOYOTA EPC SYSTEM.

*If using the current EPS group setup file...

Setup procedure

1.Copy the Group Setup Files to the Floppy Disk. (Group Setup Files: <u>TMCMSTW2¥GCGRPMEI.D</u> and <u>TMCMSTW2¥GCGRPPNC.D</u>) 2.See (8)[Copying a setup file] on (p.78).

3-3-3.EPC Data Setup

(1) Data environment setup

* Press Setup Menu.

Click Data Configuration button.



Reference: Description of the buttons in Setup Menu screen

* Data Configuration	: Setups Data Operation(DVD/Hard Disk/Server). Run this setup first after the EPC system is installed.
* Data Setup	: Setups the data with the contents created on the [Data Configuration] screen. This setup must be run whenever the data is update.
* Area/Language Setup	: Setups Data Language and Screen Language. Select an Area when the data of multiple Areas are setup.
* Group Setup	: Catalog Codes and Part Name Codes which are often searched should be registered here so that you can search the data by Group Code.
* Screen File Setup	: Use when changing a displayed title on the screen.
* Setup File Copy	: The setup Environment can be copied on other computers It will be helpful to operate multiple computers under the same environment.
* Locally Supplied Parts Setup	: Setup the data here when searching for Locally Supplied Parts.
* Price File Setup	: Setup the data here when searching Price File.
* Another Interface Application Setup	: Use when operating another system using the search results on EPC system.
* LEXUS Dealer Check	: Lexus Dealer must enter a given password so that you can search Lexus catalog.
** Clicking the "Menu" button ends th	e Setup Menu and goes back to the Main Menu.

(2) Entering Sales Area Code

- * In order to search substitution part number/procurement part number corresponding to the region, enter the 5-digit Sales Area Code.
- * Sales Area Code will be described separately
- * The ticked product numbers will not be searched.
 - If "Procr" is ticked, the procurement product number will not be displayed.
 - If "Subs" is ticked, the alternative product number will not be displayed.

(3) To setup the operation for EPC (Catalog) data





- * Select the Area you want to setup. Select the type of DVD (Area) you want to set.
- * Setup the EPC data here. Select the Area you want to setup, and setup the method for operating and the recorded place of the data for each Rec#.
- * Setup the method of your operation. Select a Server from a pull-down list box.
- ** When installed with "Client", you can select only "Server".

3-3.Setup at Client PC-13



* Select the drive where the data is set. Select the drive for the data of the server side that is allocated on (p.72) for Prior Check

(drive allocation).



* In case of Server, you can't set the drive.

(4) To setup the operation for EPC (FrameNo) data

Arroya Arrowa Arrowa<	Area	The second se	Laboratory	_		1000000	
Alexa January January <thjanuary< th=""> <thjanuary< th=""> <thjan< th=""><th></th><th>Rev Ba</th><th>Juin</th><th></th><th>The Bourse of Copy.</th><th>Output</th><th></th></thjan<></thjanuary<></thjanuary<>		Rev Ba	Juin		The Bourse of Copy.	Output	
Alea Part No. Part A. The Selection of Copy Output OPEREBAND 71 2 71 1 72 72 2 7			DEEVER	- 60	F1		
Alea Part No. Part A. The Selection of Copy Output OPEREBAND 71 2 71 1 72 72 2 7						-	
Alea Part No. Part A. The Selection of Copy Output OPEREBAND 71 2 71 1 72 72 2 7	Japan		-			의	
Alea Part No. Part A. The Selection of Copy Output OPEREBAND 71 2 71 1 72 72 2 7							
Alea Part No. Part A. The Selection of Copy Output OPEREBAND 71 2 71 1 72 72 2 7							-
Alea Part No. Part A. The Selection of Copy Output OPEREBAND 71 2 71 1 72 72 2 7							
Overtream Fri Derver Fri Derver Fri Derver Fri Derver Fri Derver		In				511	- 23
Overtream Fri Derver Fri Derver Fri Derver Fri Derver Fri Derver				V			
Protected Print Deriver De	Area	Barr Ho	(terte	_	The Ministry of Coast	Total and	
Image: State Color Fig. Image: State Color Fig. Image: State Color State Color <td>Overseas</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td>and the second se</td>	Overseas						and the second se
Pac D	Japan						-
Pac D		82	-			•	
re r r r r r r r r r r r r r r r r r r		24				•	
re r r r r r r r r r r r r r r r r r r		F1	-			•	
The Breaction of Copy Contract The Breaction of Copy Contract ti		71	-				
The Breaction of Copy Contract The Breaction of Copy Contract ti		81	1			•	*
Local file	Same Aver Code		Sete :				
Local file	177994				1	<u></u>	
Local file	100						
frain fait							
	1.0480	PLANE FLIR		-	<i>n</i>	-249	
	100 C						
		-					-
Planta chicca Ba anomphata ERC COLA solutional to sta		Deves	hire the annumi	- EBC /C			-
Please choce the appropriate EPC CD(1) you want to use		Plesse	hoce the appropria	EPC CC			

- * Perform the same operation about FrameNo DVD
- * As the number becomes bigger, the frame information will be newer. (F1 is the oldest DVD.)

(5) To setup the operation for JPIO, Local File, and Price File



 \square

- * Perform the same operation about JPIO, Local File and Price File as well.
- ** As for Local File and Price File, only operation method (HardDisk only) and the Output place can be selected.
 The actual data should be set on the [Locally Supplied Parts Setup] and [Price File Setup] screen.
- ** If Local File and Price File are set up at the server side, the data at the server side can be read by selecting the same drive with the catalog and frames as copy destination.
 In this case, performing [Locally Supplied Parts Setup] or [Price File Setup] by each client is not required.

3-3.Setup at Client PC-15



* After you set the data environment, click the "Exec" button.



- * Click the "OK" button.
- * Click the "Menu" button to return the "Setup Menu".
- * * In case of the client, as you read the data in the server, you do not need to set up the data.

3-3-4. Area / Language Setup

The Area you want to search on the EPC system and the Screen Language can be selected.

-Area	: The Area which has setup on the [Data Setup] screen can be selected.
	The Area which is selected here is searched.
-Data Language	: When the data such as Part Names, Illustration Name etc, is provided by each
	language, the Language Data which is selected here is displayed.
-Screen Languag	e : The contents on the screen are written in the Language which is selected here.

Please select "Area/Language Setup" of "SETUP MENU". ATALOG SYSTEM VLB D * Click the "Area / Language Setup" button. **Data Configuration** Avail request Side LINES Dealer Day * Select a type of DVD (Area). * Select the Language you want to display on the screen. * When you select "Local", see (p.120) for Screen / Message box Language. * Select the Data Language you want to use. * After you select each item, click the "Exec" button.

3-3-5.LEXUS Dealer Check



- * In order to use the LEXUS catalog, you need the LEXUS password.
- * In case of client, you cannot click "LEXUS Dealer Check" button. If it is set at the server, searching the LEXUS
 - catalog from the client becomes possible.

3-3-6. Procedure of Program Renewal by A1DVD

If you use EPC by server/client environment, the message like below will appear when EPC is opened in client PC after renewing the program in server PC. If you press "Yes", program will be renewed in client EPC. Then you don't need to renew the program in client PC any more.

Current version V1.0 L50 R010 → Latest version V1.0 L50 R020

 \land

After EPC the Latest Program Update has been completed, please check the EPC version by starting the "TOYOTA EPC SYSTEM". When the EPC version on the "TOYOTA EPC SYSTEM" corresponds to the version which has been announced by TMC, program renewal has been implemented correctly.

	Informat	tion of the EPO	C version		
_		OTA ELECTRONIC Back Print Help	PARTS CATALOG ST.	SHEA V1.0 L 50 R050	Main Menu]
Punction Back Print Help	PARTS CATALOG SYSTEM V1.0 L50 R050 [Hain Henu] (S: 20090101			
				TOYOTA	
ELECTR	ONIC PARTS CAT	ALOG	816150 81610F	9 3	
1	TMC Part Number Translation	\$1181A			
	Part Number Application to Models	811318 999		A A	
	New Parts List				
	Part Number List	1		N. ESIN	
	List Price		Yest // Accounts		
ļ	Save File List			6 Silve	
	Data Setup			SCHITTELE .	
	Area Language Setup	and the second s			
	Setup Menu		B C	1000 Cal	
Pro	curement Substitution Part Number history	ACE/	20		
	F3 F4 F5	on by sliding scroll bar and pres		M 20 0 Fill Fi2	
Translati	on Application NewParts PartsList	Price DSelect	Setup Area/Lana SetupMenu	Subs/Proce End	

3-3.Setup at Client PC-19

- 3-3-7. recovery
 - 1. Procedure of Program Recovery



Please end "TOYOTA EPC SYSTEM" if it is activating to recover the program.

- (1) Procedure of Program Recovery
 - 1. Program Recovery-1



* Left-double-click the "My Computer" on the desktop

2. Program Recovery-2



*Left-double-click " the destination drive where EPC has been installed "

example

When the destination drive where EPC has been installed " is "C Drive", please left-double-click "C Drive" 3. Program Recovery-3



5. Program Recovery-5

Details

Shared Documents
 My Computer

Ŧ

PAPET				1216	183
le Edit Vew Pavorites Tools	Help			ALC: NO	-
3 mi · O 1 /0	aarch 🍋 Folders 💷 •				
Alter C. (INCEPCHSIARLI				(S) (5)	2
and the second second second second		Size	Type	Date Modified	10
File and fulder Lasks	Contranslations		File Folder	10/27/2009 6:40 PM	
10 Remains this No.	and Apl Recovery Lot.	218	MS-DOO Batch File	10/27/2009 6-28 FM	
	Sept_d0.dl	6413	Application Extension	10/27/2009-6:28 PM	
🙀 How the Ne	Sexano	68.42	Application Extension	10/27/2009-6-28 PM	
Capy the file	Bepc.joca.dl	72 s.B	Application Extension	10/27/2009 6:28 PM	
Publick this file to the Web.	Tepe_mids.eve	40 KB	Appleation	10/27/2009 6:28 PM	
Ch E-mail this file	app. pro.exe	192 80	Application	10/27/2009 6:28 PM	
in Personality	Bepc_src0.dl	140 80	Application Extension	10/27/2009 6:28 PM	
	Depc_arc1.dl	84 #B	Application Extension	10/27/2009 6-28 PM	
X Delete this file	Bept_src2.dll	68 KB	Application Extension	10/27/2009-6:28 PM	
	Bec.wald	129.40	Application Extension	10/27/2009 6:28 PM	
Other Places	Bept_arc4.dl	5248	Application Extension	10/27/2009 6:28 PM	
UDIER PRACES	Bepc_inds.dl	4445	Application Extension	10/27/2009 6:28 FM	
THOPOWS	Sept_srch.dl	84 KB	Application Extension	10/27/2005 6:28 PM	
A My Documents	Sept. 317.48	7648	Application Extension	10/27/2009-6-28 PM	
Thered Econemists	Bepr. orti.dl	129.80	Application Extension	10/27/2009 6:28 PM	
	Sept_yshe.dl	68 #B	Application Extension	10/27/2009 6:28 PM	1.2
3 Thy Computer	EPCENV.BAK	348	BAK File	11/9/2009 3:21 AM	
My Nethnak Flaues	3 CPCDW.34	340	Configuration Settings	11/9/2009 3:21 AM	
A STRAIL STRAIL	epcetup.exe	1,072 88	Application	10/27/2009 6:28 PM	
100	Sepcietup.eve.manfeat	18B	MANDPEST File	10/27/2009 6:28 PM	
Details (*)	Depcticalit di	720 KB	Application Extension	10/27/2009 6-28 PM	
	Incong	148	PNG Image	10/27/2009-6-28 PM	2
	6				100

* Left-double-click the "Apli Recovery.bat"

3-3.Setup at Client PC-21

6. Program Recovery-6

Image: State Stat	 * Wait for a while. A message appears, "OK It succeeded. Press any key to continue" Please press the "Enter" key. If a message appear except "OK It succeeded. Press any key to continue", you should restart the PC and implement program recovery again.
---	--

7. Program recovery has been completed

APUT in Edit View Pavorites Tools	1940			Eß		* Program recovery has beer
						1 logiani lecovery nas been
3 Each + 🙄 🍠 🔎	Search 🎦 Polders 🛄+					completed.Please Left-click
the C:\THEPOWSIAPLI				× 🗈	60	1
and a state of the second s	Nate -	See	Type	Date Modified	10	— "X" button.
File and folder Lasks	Contranslations		File Folder	10/27/2009 6:40 PM		
B Remains that He	and Apl Recovery list	218	MS-DOS Batch File	10/27/2009 6-28 FM		
	Sept_db2.ill	6443	Application Extension	10/27/2009 6:28 PM		
All the Mar Mar Mar	Bexalia	68.42	Application Extension	10/27/2009-6-28 PM		
Copy this file	Bepc.ocs.dl	72 KB	Application Extension	10/27/2009 6:28 PM		
Publick this file to the well.	Enge_mids.eve	40 KB	Appleistion	10/27/2009 6:28 PM		
C t-mail this file	Exp. pro. eve	192 80	Application	10/27/2009 6:28 PM		
the President Plan	Bepc_src0.dl	140.80	Application Extension	10/27/2009 6:28 PM		
	Bee_mint	94 #B	Application Extension	10/27/2009 6-28 PM		
X Delete this file	Sept_sec2.dl	68 KB	Application Extension	10/27/2009 6:28 PM		
	Bec.pc3.dl	128 40	Application Extension	10/27/2009-6-28 PM		
Other Places	Sept_arit+.dt	5248	Application Extension	10/27/2009 6-28 PM		
CONFERTINGER	Bepc_src5.dl	44.65	Application Extension	10/27/2009 6-28 FM		
THOPOWS	Sept_prof.df	8435	Application Extension	10/27/2005 6:28 PM		
Any Documents	Besc. src7.4	7648	Application Extension	10/27/2009-6-28 PM		
Thered Documents	Besc.stf.dl	129 #8	Application Extension	10/27/2009 6:28 PM		
	Sept_scho.dl	68 #B	Application Extension	10/27/2009 6:28 PM	1.00	
9 Thy Computer	EPCENV.B44	348	BAK File	11/9/2009 3:21 AM		
My Nethack Flaces	GEPCENV.3M	340	Configuration Settings	11/9/2009 3:21 AM		
STRAIL PROPERTY.	@epcretup.eve	1,072 kB	Application	10/27/2009 6:28 PM		
100	Septiertup.ene.manifest	1 #B	MANDPEST File	10/27/2009 6:28 PM		
Detaily (a)	Deptickt d	720 KB	Application Extension	10/27/2009 6-28 PM		
	300.000	1 825	PNG Image	10/27/2009-6:29 PM	10	
	E.				N	

After program recovery has been completed, please check the EPC version by starting "TOYOTA EPC SYSTEM". When program recovery has been implemented correctly, the end of the version number becomes " 9 "

version before recovery : V1.0 L50 R060 [example] version after recovery : V1.0 L50 R069

4. EPC Functions To Be Localized By Users

4-1. Price File Setup-1

Description of the functions

The Local Price File prepared in the following way can be used by TOYOTA Electronic Parts Catalog System to display prices.

- * In case of including only one kind of price, prepare a text file named "PRICE". On the other hand, in case of including three kinds of price, prepare a text file named "PRICE3". See [5.File layout] for price file formats.
 - -The text file must be prepared either by a user program or by an edit program which allows editing in binary mode. The system considers that the Price File must not have an CR (carriage return), LF(line feed), and EOF(end of file) characters.
- * You can setup the Local Price File for EPC from the file prepared in diskette or HardDisk by pressing the "Refer" button and selecting the File Name. (In case of HardDisk, you can also add new data to the file or up-date necessary data in the file one by one.)
- ** A Price File Setup needs to setup a Price File on the [Data Configuration] screen beforehand. (See the section "Data Configuration" for more information)
- * Create the price file at each Dist if necessary.





4-2. Locally Supplied Parts Setup-1

Description of the functions

The Locally Supplied Parts File prepared in the following way can be used by TOYOTA Electronic Parts Catalog System to display Locally Supplied Parts as the results of Part Number Translation.

- * There are three ways to setup Locally Supplied Parts.
 - -In case of replacing one Japan Source Part Number with one Locally Supplied Part Number, prepare a text file named "LOCALP". It is the same format as that of EPC DOS version.
 - -You can also use the new format ; CSV format, which is generally supported by MICROSOFT EXCEL etc., to replace one Japan Source Part Number with one or multiple Locally Supplied Part Number. In this case, prepare a file named "LOCALP1".
 - -In case of adding Local Unique Part Numbers to TMC Part Name Code, prepare CSV format file named "LOCALP2".
 - -In case of Local Unique Illustrations and Part Numbers, prepare CSV format a file named "LOCALP3".
- * You can setup the Locally Supplied Parts for EPC from the file prepared in diskette or HardDisk by pressing the "Brows" button and selecting a file name. In case of HardDisk, you can also add new data to the file or up-date necessary data in the file one by one.
- ** A Locally Supplied Parts File Setup needs to setup a Local File on the [Data Configuration] screen beforehand. (See the section "Data Configuration" for more information)
- ** See [5.File layout] for the file format.
- * Create the Locally Supplied Parts at each Dist if necessary.

Setup procedure

Please select "Locally Supplied Parts Setup" of "SETUP MENU".





To setup an Image File ;



- * Select a path for the Locally Supplied Parts Image File to be related to the setup Local Figure(CSV).
- The Image Files contained in the selected folder will be listed up below.
- * The Locally Supplied Parts Image File on the setup Local Figure(CSV) will appear.
- * To setup the Locally Supplied Parts Image File, click the "Image Setup" or "Image" button.



- * "*" will be displayed on the left of the setup Locally Supplied Parts Image File.
- ** "*" will be displayed on the same Locally Supplied Parts Image Files which are displayed on the lower left.
- * When the setup is complete, click the "Exec" button.

4-3. Starting EPC System from Another Application-1

Description of the functions

If you activate the EPC System from another system with the condition under which the linked files are placed in the specified folder, you can search the contents of the liked files at the EPC System side, and display the search result to the screen.

The screens of the EPC System side that can be displayed during the linkage are as follows:

- 1. [Main Menu]
- 2. [Vehicle Input]
- 3. [Parts Number Translation Results]

Setup procedure

The way of using EPC System from Another Application:

- 1. You must make the "RENKEI.FIL" located on "C:\TMCEPCW3\WORK" directory as detailed in the table above.
- 2. Click on Windows Start Menu /Run and input the following command : "C:\TMCEPCW3\tmain.exe -r". (EX. In case you setup the EPC System on "C"-drive.)

*RENKEI.FIL is deleted every time the program is run.



* For layout of the linked files (RENKEI.FIL), see the next page.

<u>Configuration File layout used when starting the EPC System from Another Application :</u>

File Name: "RENKEI.FIL"(Text file format)

No	Starting column	Length	Content	Note
1	0	1	First Screen Number	 1: displaying the "Vehicle Input". 2: displaying the "Main Menu". 3: displaying the "Parts Number Translation Results".
2	1	17	VIN/VDS	
3	18	20	Model	
4	38	7	Serial Number	Frame Numbers
5	45	6	Production Date	YYYYMM
6	51	3	Color Code	
7	54	4	Trim Code	
8	58	6	PNC	
9	64	2	Quantity	
10	66		Repetition of field No.8-9	
Ν				

NOTE:

-Text file must not have CR(carriage return), LF(line feed), and EOF(end of file) characters.

4-4. Another Interface Application Setup-1

Description of the functions

The Vehicle Information and Part Number Information that have been searched for on the EPC System can used by other systems. Another Interface Application Setup has the following 3 types.

- Saving the Vehicle Information and Part Number Information in a file, and starting-up an application.
- Saving the Vehicle Information and Part Number Information in a file (not starting-up an application)
- Starting-up an application only (not interfacing the Vehicle Information and Part Number Information)

Setup procedure

Please select "Another Interface Application Setup" of "SETUP MENU".

To save the Vehicle Information and Part Number Information in a file, and start-up an application ;

For example(Sample1) :				
Another Application	: C:¥TOYOTA¥INTF.exe			
Save File	: C:¥TOYOTA¥INTF¥INTF.txt (File Type is "Fixed Len")			
To save the Vehicle Information	: Catalog Code (Item Length = 6)			
	ModelName (Item Length = 20)			
To save the Part Number Information : PNC (Item Length = 6)				
	PartNumber (Item Length = 15) *changing the Item Length.			



* Click the "Another Interface Application Setup" button.



- * Click the "Add" button.
 - When Another Interface Application has been already setup, the contents are displayed on the screen.

lana -		~	The Hanne			
a Norman (No				Fin Tone F Final Lange F Demine	F	
Vehica differentian	But Laryth		-	(Sector voice a str	Ser Lange	
Preterici	*****	14				
CatalogCode						100
Multilitate.		20	COMPANY OF			100
Muler Pro/Ente		*				
	1000	-7		-	Call I	
Fuel Rottine Effortation:	Rent Langth	10071		Saterlind Part Hamilton 1975	Ben Langfe	
PuC			and the second			
Perblatker	-	12	1.000			1.0
Partoste		40 2 12				
Qty Pi-Te						
10.1E			and the second			
Fride						

screen will appear.

* [Layout of Another Interface Application]

- * Enter the Pattern Name you want to setup here.
- * To setup an application to be started-up, click the "Brows" button.
 - You can enter it directly. Be sure to enter a Drive Name first.
 - EX.) If you start-up " C:¥TOYOTA¥INTF.exe",



4-4. Another Interface Application Setup-3





- * Enter a File Name to be saved.
- * Select a File Type to be saved.
- ** When you selected Delimited, enter a Delimiter.
 - EX.) If you save the information for "C:\TOYOTA\INTF\INTF.txt", you input the Filename as "INTF.txt".



- * Setup a File Layout to be saved.
- * Select the Vehicle Information to be saved from the list on the left screen, and click the "Add" button.
 - The selected item will be added to the list on the right screen.
 - The data will be output in order of the item selected.
- You can change the Item Length.
- * Select the Part Number Information to be saved from the list on the left screen, and click the "Add" button.
 - The selected item will be added to the list on the right screen.
 - The data will be output in order of the item selected.
- You can change the Item Length.
- ** "Sample1" File Layout is on (p.101)

4-4. Another Interface Application Setup-5



* After the layout is complete, click the "Fix" button.



- * The setup Pattern Name will appear.
- * Select the Pattern and click the "Exec" button to end the setup and go back to the [Main Menu] screen.

Now the setup is complete.


INTF.exe

* If the [F6 Intf] button is actually pressed in "Parts Number Translation Results"

To save the Vehicle Information and Part Number Information ;

For example(Sample2):	
Save File	: C:¥TOYOTA¥INTF¥INTF.CSV (File Type is "Delimited")
To save the Vehicle Information	: VIN (Item Length = 17)
	Catalog Code (Item Length $= 6$)
To save the Part Number Information	: PNC (Item Length = 6)
	PartNumber (Item Length = 12)



- * Click the "Add" button.
 - When Another Interface Application has been already setup, the contents are displayed on the screen.



- * [Layout of Another Interface Application] screen will appear.
- * Enter the Pattern Name you want to setup here.
- * To setup a folder where a file is created, click the "Brows" button.
- You can enter it directly. Be sure to enter a Drive Name first.

EX.) If you create " C:¥TOYOTA¥INTF¥INTF.CSV",

C:¥TOYOTA¥INTF





- * Enter a File Name to be saved.
- * Select a File Type to be saved.
- ** When you selected Delimited, enter a Delimiter.
 - EX.) If you save the information for "C:¥TOYOTA¥INTF¥INTF.CSV", you input the Filename as "INTF.CSV".



- * Setup a File Layout to be saved.
- * Select the Vehicle Information to be saved from the list on the left screen, and click the "Add" button.
 - The selected item will be added to the list on the right screen.
- The data will be output in order of the item selected.
- You can change the Item Length.
- * Select the Part Number Information to be saved from the list on the left screen, and click the "Add" button.
 - The selected item will be added to the list on the right screen.
 - The data will be output in order of the item selected.
 - You can change the Item Length.
 - ** "Sample2" File Layout is on (p.107).



* After the layout is complete, click the "Fix" button.

Eventra Electricolo: Parite Cafellos (VETER Venter Danmar Energia Au- enter Bast First Help	
The same lists taken tak	
Aberlan Fil	
Par Tana	Bastina
Sended versige threader. Bei Leigh	Similar Fel Neter Hondon
Select the sect p	recess from the function bulletes.

- * The setup Pattern Name will appear.
- * Select the Pattern and click the "Exec" button to end the setup and go back to the [Main Menu] screen.

Now the setup is complete.

* If the [F6 Intf] button is actually pressed in "Parts Number Translation Results"



To start-up an application only ;

For example:

Another Application : C:\TOYOTA\INTF.exe



- * Click the "Add" button.
 - When Another Interface Application has been already setup, the contents are displayed on the screen.



- * [Layout of Another Interface Application] screen will appear.
- * Enter the Pattern Name you want to setup here.
- * To setup an application to be started-up, click the "Brows" button.
- You can enter it directly. Be sure to enter a Drive Name first.
 - EX.) If you start-up "C:¥TOYOTA¥INTF.exe",

C:¥TOYOTA¥INTF.exe

111

4-4. Another Interface Application Setup-12



- * Select an application to be started-up.
 - Without clicking the "Brows" button, this screen won't appear.
- * After you selected the application, click the "Open" button.



* After the layout is complete, click the "Fix" button.



- * The setup Pattern Name will appear.
- * Select the Pattern and click the "Exec" button to end the setup and go back to the [Main Menu] screen.

Now the setup is complete.

* If the [F6 Intf] button is actually pressed in "Parts Number Translation Results"



Another Interface Save File :

Sample1: INTF.txt

File Format: (fixed text format)

No	Starting column	Length	Content	Note
1	0	6	Catalog Code	
2	6	20	Model Name	
3	26	6	PNC	
4	32	15	PartNumber	Length is changed.(default = 12)
5	47		Repetition of field No.3-4	
Ν				

Sample2: INTF.CSV File Format: (CSV format)

No	Length	Content	Note
1	17	VIN	
2	6	Catalog Code	
3	6	PNC	
4	12	PartNumber	
5		Repetition of field No.3-4	
Ν			

Description of the functions

Catalog Codes and Part Name Codes which are often searched can be registered all together. This setup enables you to search the data by Group Code. If you don't register a Catalog Code, the Group becomes effective for all Catalog Codes you may input in the "Vehicle Input" screen. In case the Catalog Code list is not left blank, the Group becomes effective when the Catalog Code is input in the "Vehicle Input" screen.

- When performing the operation of the client/server, the group code data will be saved at the server side.

Setup procedure Please select "Group Setup" of "SETUP MENU". Click the "Group Setup" button. Locally Supplied Parts Ref. - If one terminal is setting up the group code while performing the operation of the client/server, the following message will be displayed: It is not possible to use it because it is operating it with another client. LOUX Dealer Charl Please wait until the group setup is complete. Scines in the later Selective Dates * Enter the Group Code you want to create. - Group Code should be 3-digit. - When the input Group Code is already registered, the details will appear. * Enter a Group Name after you enter the Group Code, and press the "Enter" key.



- * Type a Part Name Code, and press the "Enter" button.
 - If you enter a 5 or 6-digit Part Name Code, the Part Name will appear automatically.
 - Part Name Code : Enter * after at least 3 letters input of Part Name Code.
- * After the Part Name Code is entered, click the "Add" button.
 - Both Part Name Code and Part Name will appear in the list.
- If you have multiple Part Name Codes to be registered repeat the same operation.



- * Enter the first 3-digit Catalog Code and click the "Add" button.
 - The input data will appear.
 - If you have multiple Catalog Codes to be registered, repeat the same operation.
 - You can skip this input.

* After all setups are completed, click the "Exec" button.

To change the contents of a registered Group ;



* Click the "List" button.

- If you know the Group Code you want to change, enter it directly.



- * The list of the registered Groups will appear. Select the Group you want to change, and click the "Exec" button or press the "Enter" key.
 - If you enter a Group Code directly, this screen won't appear.





To delete a registered Group ;



- * Check that the Group Code you want to delete is displayed.
- * Click the "Del" button to delete the displayed Group Code Data.

To delete a Part Name Code from a Group ;



- * Select the Part Name Code you want to delete.
- * Click the "Del" button to delete the selected Part Name Code from the Group.

To delete a Catalog Code (the first 3-digit) from a Group ;

10YOTA ELECTRONIC FARTS CATALOG SYSTEM Vice	olos Dine Setel		K(1)
autise Ball Fird Help			
Orbid Calle			
Croig Code (DI) (Un) (Un)			
Cerrigition (chourt			
Part Have Cale	and the second sec	Calaby Coactive Red 3	0
Part Name Com			
Fulltana			
and the second second	1		
OUTT CASHET NT. ENDINE OVERWALK	the second s		
DRITE GASHETHIT, ENGINE VALVE OFINE			
and the second s			
			1100
			1 Sec. 1
		and the set	1.00
			1000
			1
	Enter & Part Name Code 315 went to register a	n The group	

- * Select the Catalog Code (the first 3-digit) you want to delete.
- * Click the "Del" button to delete the selected Catalog Code (the first 3-digit) from the Group.

Reference

System Limits (Group Setup);

Please consider the following system limits in Group Setup.

Limit is set on ;	Limit
Part Name Codes inputted on Group Setup	100
Catalog Codes inputted on Group Setup	50
Group Codes	999

4-6. Screen / Message box Language-1

Description of the functions

Changing screen display items (screen items, buttons, etc.)

The EPC screen titles and messages are provided in English, Japanese, French, German and Spanish by TMC. Use this setup when using the data written in another language and changing the titles on the screen.

-About the Screen Language Setup, you should go to the [Area/Language Setup] screen.

*NOTICE: Please note that if the text you input was too long, it might get truncated on screen, as in the following

cases: case 1: The rightmost letters of the title are not visible.

case 2: The rightmost letters of the message are not visible.

case 3: The text inside buttons become truncated on its left and right.

case 4: On the Group Title (ex. Letter of "VIN/VDS" on "Vehicle Input"), some characters aren't displayed. Changing the guidance, messages and help

By directly editing the files for each language, you can change the contents that are displayed on the screen.

Setup procedure

Select "Area/Language Setup" and select "Local" in "Screen Language" (refer to P.58).



Please select "Screen Setup" of "SETUP MENU".



* Click the "Screen File Setup" button.

4-6. Screen / Message box Language-2

Press B	0	International Description of the local data and the	
Patiens			
Patiens		Press and Press	
AVDAR AVDAR Vite Non Althes Althe			
FVR FXRed			
Fibbe Fibbe Fibbe Fibre			- I I I I I I I I I I I I I I I I I I I
Aras Presid Priverad Pr			
Pricesope Prine			
Pricesope Prine		Publicat	
Prime			
Price Prise			
Pilyes Pilaken Pilaken Pilaken Pilyes			
Pilles Pilles Pilles Pilles Pilles Pilles Pilles Pilles Pilles Rol Rol Rol Rol Rol Rol Rol Rol Rol Rol		TFuet	
POLane POlane POlane POlane POlane Polan Pola			
PDDa+ PDDa+ PDDahan PDDahan PDDahan PDDah PDDah PDDah PDDah PDDah PDDah PDDah PDDah PDDah PDDah PDDah PDDah PDDah PDDah PDDah PDDah PDDah PDDAH PDDAH		Phone	
Pitradikan		FULLOW	-1
P2Solution P2Bard P2Bard P2Bar P2Bar P2Bar P2Bar P2Bard P2Bard P2Bard P2Bard P2Bard P2Bard P2Bard P2Bard P2Bard P2Bard P2Bard		Fibles	-
H Paul H Paul Polia		Plotalter	-
Pilae Pilae Rat Rat Rat Rat Rate Rate Rate Rate R		Pittodiska	
Peter Kon Polin Polini Tome Tome Tome Tome Tome		Filture	
Ein Fait Täme Fäund Fäund Fäund Fäund Fäund		Prime	
P24 P2ms Plans Plans Plans Files Files		Filmt	
Zama Zama Zizana Zizana Zizana Zizana			
70mi Frees Trees Time Time Yime		F2.4	
Flows Flows Flows Views			
P2mm P20mm P20mm		22/mpd	
Pilon Yana		Frees	
YZum		12 mil	
		Filtern	
1 Marc 20			
		* Bort	21
	No. of Concession, Name	Darge by Screen Text and 200 the event batter.	NAME OF TAXABLE PARTY.
	and the second second		



- ** The list is classified as follows:
 - Function Key
 - -> Common(Function Key)
 - Menu Item
 - -> Common(Menu)
 - Items on each screen
 - -> Each screen name



- * The items you can change will appear.
- * Select the Screen Text you want to update and press the "Enter" key.



- * Enter the content you want to update with, click the "Exec" button.
 - To go back without updating the data, click the "Cancel" button.



- * "*" is displayed on the left of the changed Screen Text.
- ** If you have any other item to be changed, repeat the same operations.
- * Click the "Exec" button to reflect your changes to the system.

* When "*" has disappeared, the update process is complete.

Close the EPC and restart it, and your translation will be reflected.

When you need to change

(1)Operation and Error Messages

- 1. Edit "dencata_??.ini" with a text editor. (??:See *1 for more details. dencata_??.ini is located on X:¥TMCEPCW3¥APLI¥translations directory.)
- 2. Basic rule for the message file is as follows; You must change messages after "=". You can't add a new message ID and change message ID. The text of a message should be written on one line (it cannot include carriage returns). Message ID including "MG" are guidance messages. Message ID including "ME" are error messages. Message ID including "MB" are Message Box guidances. (See Appendix B for more details.)
- 3. After editing, restart the TOYOTA Electronic Parts Catalog System.

(2) Help

- Edit GXXXXX??.txt by use of an edit program. (XXXXX means Screen ID. See < the Help File Name and the Screen >(P.129) for more details. ??: See *1 for more details.) (GXXXXX ??.txt is located on X:¥TMCEPCW3¥HELP directory.)
- *1: ?? means "Screen Language" selected on "Area/Language Setup". (??:"01" as English, "02" as Japanese, "03" as French, "04" as Germany, "05" as Spanish and "99" as Local.) When you selected English as "Screen Language" on "Area/Language Setup", you must edit "01" files.

5. For Distributors (File layout)

< Local Price File >

-In the case of including one kind of price.

PRICE(text file format)

Starting column	Length	Content	Note
0	12	Part Number	
12	8	Price	Including "," or "."
20	10	Remarks	
30	20	Part Name	

NOTE :

- -"," in 'Price' should be specified by three digits.
- -"." in 'Price' means a decimal point.

-'Price'(including 'List Price') field allows only number except "," and ".".

-In the case of including one kind of price.

PRICExxx.CSV(CSV file format)-----xxx is a sequential number starting with '001'.

Length	Content	Note
Between 10 and 12	Part Number	
Max 8	Price	Including "," or "."
Max 10	Remarks	
Max 20	Part Name	

NOTE :

- "," in 'Price' should be specified by three digits.
- "." in 'Price' means a decimal point.
- 'Price'(including 'List Price') field allows only number except "," and ".".
- Each data must be divided by comma(,), but it is not necessary to add double quotation mark("").
- In the case of including comma(,), the data must be added double quotation mark("").
- You must make sorted price data by the key of Part Number.
- * Also, when the several price files are created, the product numbers between the price files should be in ascending sequence.
- CSV file format is generally supported by Microsoft Excel etc.

-In the case of including three kinds of price.

PRICE3(text file format)

Starting column	Length	Content	Note
0	12	Part Number	
12	8	List Price	Including "," or "."
20	8	Trade Price	Including "," or "."
28	8	Cost Price	Including "," or "."
36	10	Remarks	
45	20	Part Name	

NOTE :

-"," in 'Price' should be specified by three digits.

-"." in 'Price' means a decimal point.

-'Price' (including 'List Price', 'Trade price' and 'Cost Price') field allows only number except "," and ".".

-In the case of including three kinds of price.

PRICE3xxx.CSV(CSV file format)-----xxx is a sequential number starting with '001'.

Length	Content	Note
Between 10 and 12	Part Number	
Max 8	Price Price	Including "," or "."
Max 8	Trade Price	Including "," or "."
Max 8	Cost Price	Including "," or "."
Max 10	Remarks	
Max 20	Part Name	

NOTE :

- "," in 'Price' should be specified by three digits.
- "." in 'Price' means a decimal point.
- 'Price' (including 'List Price', 'Trade price' and 'Cost Price') field allows only number except "," and ".".
- Each data must be divided by comma(,), but it is not necessary to add double quotation mark("").
- In the case of including comma(,), the data must be added double quotation mark("").
- You must make sorted price data by the key of Part Number.
- * Also, when the several price files are created, the product numbers between the price files should be in ascending sequence.
- CSV file format is generally supported by Microsoft Excel etc.

< Locally Supplied Parts File >

-In the case of replacing one Japan source part number with one locally supplied part number.

Starting columnLengthContentNote012Japan source part numberPart number to be replaced by
locally supplied part number1212Locally Supplied Part Number2420Remarks

LOCALP(Text file format, it is the same format as EPC DOS version)

-In the case of replacing one Japan source part number with one or multiple Locally supplied part numbers.

LOCALP1(CSV file format)

Length	Content	Note
Between 10 and 12	Japan Source part Number	
Between 10 and 12	Locally Supplied Part Number	
4	Production Date(From)	YYMM
4	Production Date(To)	YYMM
Max 30	Remarks	

NOTE :

-Each data must be divided by comma(,), but it is not necessary to add double quotation mark("").

-In the case of including comma(,), the data must be added double quotation mark("").

-You can make multiple data with the key of Japan Source Part Number.

-CSV file format is generally supported by Microsoft Excel etc.

-In the case of adding Local unique part numbers to TMC part name code.

LOCALP2(CSV file format)

Length	Content	Note
6	Catalog Code	
Max 6	TMC part name code	
Between 10 and 12	Local Unique Part Number	
4	Production Date(From)	YYMM
4	Production Date(To)	YYMM
Max 30	Remarks	

NOTE :

-Each data must be divided by comma(,), but it is not necessary to add double quotation mark("").

-In the case of including comma(,), the data must be added double quotation mark("").

-You can make multiple data with the key of Catalog Code and TMC part number code.

-CSV file format is generally supported by Microsoft Excel etc.

-In the case of local unique illustrations and part numbers.

LOCALP3(CSV file format)

Length	Content	Note
6	Catalog Code	
4	Fig No	
Max 30	Fig Name	
Max 12	Image File Name	File name of Local unique illustration
Between 10 and 12	Local Unique Part Number	
4	Production Date (From)	YYMM
4	Production Date (To)	YYMM
Max 30	Part Name	
Max 30	Remarks	

NOTE :

-Each data must be divided by comma(,), but it is not necessary to add double quotation mark("").

-In the case of including comma(,), the data must be added double quotation mark("").

-You must make multiple data with the key of Catalog Code, Fig No, Fig Name and Image File Name.

-Image data must be made according to the bitmap format (BMP), JPEG format (JPG or JPEG) and PNG format (PNG). Image data size is free. But if image is bigger than display area, the image is displayed with a scale-down.

-CSV file format is generally supported by Microsoft Excel etc.

< the Help File Name and the Screen >

Help Files are located on X:¥TMCEPCW3¥HELP directory.

Explanation of the Help File's name: G1010001.txt

G<u>10100</u>01 : 10100 means the Screen ID.

G1010001.: 01 means "Screen Language" selected on "Area/Language Setup".

("01" as English, "02" as Japanese, "03" as French, "04" as Germany, "05" as Spanish and "99" as Local.)

Screen ID:

Screen ID	Screen Name	Screen ID	Screen Name
10100	Main Menu	50100	Parts Number Translation Results
20100	Part Number Application to Models	50110	List Price
20110	Data Setup Status	50120	Part Number Input
20200	New Parts List	50130	Data Save
20300	Part Number List	80100	Abbreviation Search
20401	List Price	80200	Vehicle Information
20500	Save File List	80400	Help
30101	Vehicle Input	80500	Substitution/Procurement Part Number history
30110	Catalog Code Select	90100	Setup Menu
30120	Characteristics	90200	Data Setup
30130	Vehicle Model Select	90210	Data Configuration
30200	Search Route	90220	System Configuration
30300	Illustrated Index	90300	Area/Language Setup
30400	Figure	90400	Setup File Copy
30500	Parts Index	90500	Locally Supplied Parts Setup
30600	Parts Figure	90510	Image Data Setup
30700	PNC Input	90600	Price File Setup
30710	PNC Select	90700	LEXUS Dealer Check
40100	Group Search	90800	Group Setup
40200	Group PNC Search	90810	Group List
40300	LOCAL Figure Number List	90900	Screen File Setup
40400	Detail Illust of LOCAL Parts	90910	Screen Text Edit
40500	J-PIO List	91000	Another Interface Application
40510	Campaign Select	91010	Layout of Another Interface Application
40600	Photo of J-PIO	91100	Log

Message List :

TOYOTA Electronic Parts Catalog System has six Message Files.

dencata_01.ini : English is "Screen Language" selected on "Area/Language Setup".

dencata_02.ini : Japanese is "Screen Language" selected on "Area/Language Setup".

dencata 03.ini : French is "Screen Language" selected on "Area/Language Setup".

dencata 04.ini : Germany is "Screen Language" selected on "Area/Language Setup".

dencata_05.ini : Spanish is "Screen Language" selected on "Area/Language Setup".

dencata_99.ini : Local is "Screen Language" selected on "Area/Language Setup".

Explanation of the contents: Sample) MG101000=Select a job.

MG <u>10100</u> 0	10100 is the Screen ID (See Screen ID List on [p.128]).
MG10100 <u>0</u>	0 is the serial Number.
Select a job.	This is the Message.
M <u>G</u> 101000	G:guidance / B:message box / E:error

List of English Message (dencata_01.ini):

MB0000001=%1 isn't set on the CD# setup.

MB0000002=CD is updated. Go back to the [Main Menu] and execute the setup. MB0000003=Insert the latest %1 (%2) CD to the CD drive. MB0000004=CD drive is powered off or CD isn't set. Set the %1 (%2) CD. MB0000005=%1 (%2) data isn't set correctly. Set the appropriate CD. MB0000006=Data Setup is running on the sever. Go back to the [Main Menu] and wait for the setup to be completed. MB0000007=%1 (%2) data isn't set correctly. Check the setup. MB0000008=Insert the latest %1 (%2) CD to the CD drive. MB0000009=%1 data isn't set correctly. Set the appropriate CD. MB0000010=%1 (%2) data isn't set correctly. Check the setup. MB0000011=Insert the New Layout %1(%2) CD to the CD drive. MB0000020=European MB0000021=General MB0000022=USA MB0000023=Japanese MB0000024=Japanese MB0000025=Over Sea MB0000030=EUR MB0000031=GEN MB0000032=USA MB0000033=JPN MB0000034= MB0000035= MB201008=Do you want to print the Part Number Application to Models? MB202001=The number of new part numbers exceeded 300. Press "Yes " to continue or " No " to end. MB202002=Do you want to print the New Parts List? MB203001=Do you want to print the Part Number List? MB204101=Do you want to print the List Price? MB205001=Are you sure you want to delete the selected Save Data? MB301101=Do you want to print the Catalog Code Select? MB301201=The information for the specified Characteristic Sign couldn't be acquired. MB301301=Do you want to print the Vehicle Model Select? MB304001=Do you want to print the Figure? MB306001=Do you want to print the Figure? MB405001=Do you want to print the J-PIO? MB406001=Do you want to print the Photo of J-PIO?

MB501001=Are you sure you want to delete the unspecified Part Numbers? MB501003=Do you want to print the Parts Number Translation Results? MB501004=Save handling of data was completed. $\frac{1}{2}$ (SaveDataNo = %1) MB804001=Do you want to print the Help File? MB902001=Is it OK that the CD you set is older than the setup CD ? MB902002=Not enough space in drive. MB902003=%1 is set up. Is it all right? MB902101=Are you sure you want to cancel this setup? MB902102=Setup has been completed. MB902103=The setting of the server cannot be referred to.¥nEnd the EPC system and check the setting of the network drive. MB902104=The following data is not set up to the server.¥n%1¥nMay I complete the setting? MB904001=Are you sure you want to write over a read-only File? MB904002=Group Code Information cannot be found. Do you want to copy the next File?(Cancel/Retry/Ignore) MB904003=Environmental Information cannot be found. Do you want to copy the next File?(Cancel/Retry/Ignore) MB904005=Group Code Information cannot be found. Do you want to try again? (Cancel/Retry) MB904006=Environmental Information cannot be found. Do you want to try again? (Cancel/Retry) MB904007=Screen Information cannot be found. Do you want to try again? (Cancel/Retry) MB905001=Local File has been already existed. Do you want to add the data? MB905002=Do you have the next data? MB905003=Local File Setup has been completed. MB906001=Price File has been already setup. Do you want to setup again? MB906002=Do you have the next data? MB906003=Price File Setup has been completed. MB908001=Are you sure you want to delete this Group Code? MB910001=Are you sure you want to delete the current setup Pattern? MB910002=The selected Pattern is interfaced. Are you sure you want to delete it? MB910003=Are you sure you want to release the current Interface Setup and go back to the [Setup Menu]? MB910004=Are you sure you want to setup the Interface with the selected Pattern? MB910101=Layout has been fixed by the value on this screen MB911001=Do you want to print the Log File? MB911002=Check your e-mail settings and try again. MBPrint01=Printing has been finished. MBPrint02=Process isn't executed. MBPrint03=Constructor cannot be found. MBPrint04=Command Use. MBPrint05=Printer Set-up Information is wrong. MBPrint06=Identifer cannot be found. MBPrint07=Error occurred while opening a file. MBPrint08=Printer is not ready. Check the printer. MBPrint09=Layout for Input File is wrong. MBPrint10=Error occurred while reading Image Files. MBPrint11=Image File cannot be found. MBPrint12=An application error has occurred. ME101001=Missing the price file. Execute the [Price File Setup] to set up the price file. ME101002=Execute the set up. ME101003=No save file can be found. ME201001=Select the Part Number you want to delete. ME201002=Enter a part number and press enter key. ME201003=You can enter maximum of 10 Part Numbers. ME201004=Enter 10 or 12 digits part number(s), and press F10. ME201007=This Part Number has been already entered. ME201009=Data not available. ME201101=Select Rec#s.

ME202002=Appropriate data cannot be found. Check the input data. ME202003=Enter a Date. ME202004=Catalog Code isn't entered. Check your input and press F10 key. ME202005=Incorrect Date entered. Check your input and click "Exec" button. ME202007=Appropriate vehicle cannot be found with the information you provided. Check your input and try again. ME203001=Appropriate data cannot be found. Check the input data. ME203002=Appropriate data cannot be found. Check the input data. ME203003=Part Name Code/Part Name isn't entered. Check your input and press F10 key. ME204101=Specified part number does not exist. Check your input and try again. ME204102=The entered Part Number has been already searched. Check your input. ME204103=Specified part number does not exist. Check your input and try again. ME205001=Cannot be executed. Select save file(s) and select the next function by pressing an appropriate PF key. ME205002=Select only one save file and press F10 key. ME301001=Some items have been already fixed. Check your input. ME301002=Enter VIN, catalog code or model and press enter key. Add necessary information and press F10 key. ME301003=Appropriate vehicle cannot be found with the information you provided. Check your input and try again. ME301004=Appropriate vehicle cannot be found with the information you provided. Check your input and try again. ME301005=Production date cannot be determined with this frame number.Enter the production date. ME301006=Vehicle Information cannot be found in the specified file. ME301007=No save file can be found. ME301101=Catalog Code isn't selected. Select appropriate data and press F10 key. ME301201=Appropriate vehicle cannot be found with the information you provided. Check your input and try again. ME301301=Model isn't selected. Select appropriate data and press F10 key. ME302001=Select Illustrated Index Group(s) and press F6 key. ME302002=Specified figure number does not exist. Check your input and try again. ME302003=Specified part name code does not exist. Check your input and try again. ME302004=Specified part number does not exist. Check your input and try again. ME302005=Specified figure number does not exist. Check your input and try again. ME302007=Specified part name code does not exist. Check your input and try again. ME302008=Part isn't selected. Check your selection and try again. ME302009=Specified part number does not exist. Check your input and try again. ME302010=Appropriate data cannot be found. Check the input data. ME302011=Specified group code does not exist. Check your input and try again. ME302012=Specified figure number does not exist. Check your input and try again. ME302013=Specified part name code does not exist. Check your input and try again. ME302014=Specified part number does not exist. Check your input and try again. ME302015=Specified group code does not exist. Check your input and try again. ME302016=Appropriate data cannot be found. Check the input data. ME303001=Select figure numbers and press F10 key. ME304001=Select part name codes or part numbers to be translated and press F10 key. ME304002=Maximum number of 999 for part name codes has been reached. No more part name codes can be selected. ME304003=Invalid data is entered. Only numeric is allowed. ME305001=Data isn't selected. Select a Part and press F10 key. ME306001=Select part name codes or part numbers to be translated and press F10 key. ME306002=Maximum number of 999 for part name codes has been reached. No more part name codes can be selected. ME306003=Select an image from the Illustrated Index list. ME307001=Specified Part Name Code/Part Name doesn't exist. Check your input. ME307002=Specified Part Name Code/Part Name doesn't exist. Check your input. ME307003=Enter part name codes or part name to be translated and press F10 key. ME307004=Data isn't selected. Select appropriate data and press F2 key. ME307005=Specified part name code does not exist. Check your input and try again. ME307006=Invalid data is entered. Only numeric is allowed. ME307007=Maximum number of 999 for part name codes has been reached. No more part name codes can be selected.

ME401001=Select a group code by sliding scroll bar and pressing enter key. ME401002=Appropriate data cannot be found. Check the input data. ME403001=Select figure numbers and press F10 key. ME404001=Appropriate illustration cannot be found for the information provided. ME404002=Select Local Part Numbers to be translated and press F10 key. ME404003=Invalid data is entered. Only numeric is allowed. ME405101=Appropriate data cannot be found. Check the input data. ME405102=Campaign Name isn't selected. Select a Campaign Name and press F10 key. ME406001=Appropriate illustration cannot be found for the information provided. ME501001=Part Number isn't selected. Select a Part Number and try again. ME501002=Missing the price file. Select [Price File Setup] to set up the price file. ME501003=Appropriate vehicle cannot be found with the information you provided. Check your input and try again. ME501004=The Fig-No for the specified Part Name Code cannot be found. Check your input. ME501005=Invalid value. Enter correct information. ME501006=Another Model cannot be searched any more. Save the data and execute the [Part Number Translation] from the [Main Menu]. ME501201=Incorrect Part Number entered. Check your input. ME501202=Invalid data is entered. Only numeric is allowed. ME801001=Data doesn't exist. Enter an abbreviation and press F6 key.Press ESC key to exit from the abbreviation mode. ME801002=Appropriate data cannot be found. Check the input data. ME801003=99 Abbreviations are displayed. Clear them and try again ME804001=Help file cannot be found. Return to the Main Menu and execute the Program Setup. ME805001=Specified part number does not exist. Check the input data. ME805002=Appropriate data cannot be found. Check the input data. ME901000=It is not possible to use it because it is operating it with another client. ME902101=Source cannot be selected. ME902102=Output cannot be selected. ME902103=Source and Output cannot be selected. ME902104=The same drive is selected for Source and Output. ME902105=Enter Sales Area Code that Distributor provided. ME904001=The disk cannot be written on. Check the disk. ME904002=Not enough space in drive. ME904004=File couldn't be opened. ME904005=The attributes of the File couldn't be changed. ME904006=File couldn't be deleted. ME906001=Cannot be executed. Price file not found or price file size is invalid. ME908001=Specified part name code does not exist. Check your input and try again. ME908002=Enter part name codes for the group code and press F10 key again. ME908003=This Part Name Code has been already registered. Check your input. ME908004=This Catalog Code has been already registered. Check your input. ME908005=The number of group codes exceeded 999. If you want to add a new group code, delete an unnecessary group code. ME908006=100 Part Name Codes have been already registered. Check your input. ME908007=50 Catalog Codes have been already registered. Check your input. ME908008= ME910001=Select the Pattern you want to edit from the Pattern Setup. ME910002=Select the Pattern you want to delete from the Pattern Setup. ME910003=Select the Pattern you want to display from the Pattern Setup. ME910004=Select the Pattern you want to interface with from the Pattern Setup. ME910101=Select the Vehicle Information you want to add from the Vehicle Information list. ME910102=Select the Vehicle Information you want to delete from the selected Vehicle Information list. ME910103=Select the Part Number Information you want to add from the Part Number Information. ME910104=Select the Part Number Information you want to delete from the selected Part Number Information. ME910105=Pattern Name isn't entered. Enter a Pattern Name and press F10 key. ME910106=This Pattern Name has already existed. Enter another Name and press F10 key. ME910107=Enter either Interface PG or Interface File, and press F10 key.

ME910108=Enter both Folder for Interface File and File Name, and press F10 key. ME910109=File Name including [\\;;*?\"<>|] isn't allowed to enter. Check your input. ME910110=Add either Vehicle Information or Part Number Information to be saved in the Interface File, and press F10 key. ME910111=Incorrect numeric data entered. Enter an item length in range of between "1" and "999". ME911001=Log File cannot be found. MG101000=Select a operation by sliding scroll bar and pressing enter key. MG201000=Enter part numbers and press F10 key. MG201005=Searching data from CD or harddisk. Please wait. MG201006=Select the next function by pressing an appropriate PF key. MG201100=Set Rec#s. MG201102=Check a Rec#. MG202000=Enter both Catalog Code and Date, and press F10 key. MG202001=Searching data from CD or harddisk. Please wait. MG202002=Select the next function by pressing an appropriate PF key. MG203000=Enter a part name or a part name code and press enter key. MG203001=Searching data from CD or harddisk. Please wait. MG203002=Select the next function by pressing an appropriate PF key. MG204100=Enter a part number and press enter key. MG205000=Select one save file and select the next function by pressing an appropriate PF key. MG301000=Enter VIN, catalog code or model and press enter key. Add necessary information and press F10 key. MG301100=Select a catalog code by sliding scroll bar and pressing enter key. MG301102=You are not regarded as a Lexus dealer. You cannot use Lexus catalogs. MG301200=Select vehicle characteristics by sliding scroll bar and press F10 key. MG301201=Check a Characteristic Sign. MG301300=Select a model code by sliding scroll bar and pressing enter key. MG302000=Select a Search Route. MG303000=Select figure numbers by either sliding scroll bar or placing mouse on the illustration and press F10. MG304000=Select PNCs or P/Ns with scroll bar or mouse or click the right button of mouse to display a detailed illustration. MG305000=Select a Part and press F10 key. MG306000=First, select an Illustrated Index Image and select either Part Name Code or Part Number, and then press F10 key. MG307000=Enter either Part Name Code or Part Name, and press F10 key. MG307100=Select PNCs by sliding scroll bar and pressing enter key. Press F8 when all the selection from this list is made. MG401000=Select a group code by sliding scroll bar and pressing enter key. MG402000=Select a operation by sliding scroll bar and pressing enter key. MG403000=Select figure numbers and press F10 key. MG404000=Select a Local Part Number and press F10 key. MG405001=To print this list, select "Print>List Prnt" from the menu. MG405101=Select a Campaign Name and press F10 key. MG406001=To print this photo, select "Print>List Prnt" from the menu. MG501000=Select the next function by pressing an appropriate PF key. MG501001=Enter vehicle data or press F3 to get a list of vehicle characteristics for part number retranslation. MG501002=Executing part number translation. Please wait. MG501003=Searching has been completed. MG501100=Select the next function by pressing an appropriate PF key. MG501200=Enter part name codes and quantities and press F8 key. MG801001=Enter abbreviation and press F6 key. MG801002=Enter abbreviation and press F6 key. MG802001=Check the Vehicle Information. MG804001=To print this Help, select "Print>List Prnt" from the menu. MG805001=Enter a part number and press enter key. MG805002=Please press F1 key to retrieve again. MG805003=Enter a part number and press enter key.

MG901000=Select one item to be set up by sliding scroll bar and press the enter key. MG902000=Please choice the appropriate EPC CD(s) you want to use. MG902001=Insert the latest %1 to the CD drive and press "Enter" key. When you want to cancel, press "Esc" key. MG902002=%1 is being setup now. MG902003=The data cannot be copied. Check the [Data Configuration]. MG902004=Insert the setup %1 to the CD drive and press "Enter" key. When you want to cancel, press "Esc" key. MG902005= MG902006=Insert the New Layout %1 to the CD drive and press "Enter" key. When you want to cancel, press "Esc" key. MG902101=Please choice the appropriate EPC CD(s) you want to use. MG902102=Select the System Environment and press F8 key. MG903000=Setup the necessary items and press F8 key. MG904000=Select both File and Drive, and press F6/F8 key. MG904001=Please wait. MG905000=Select a File Type and click "Brows" button to specify a file. MG905001=Press F8 key. MG905002=Please wait. MG905100=Select a folder for the Image Data and press F6 key. MG905101=Please wait. MG906000=Select a File Type, and click "Brows" button to specify a file. MG906001=Press F8 key. MG906002=Please wait. MG907000=Enter the LEXUS dealer password given for this set of CDs and press F8 key. MG907001=The Password is wrong. You can't use a Lexus catalog. MG907002=Please wait. Your data is being inquired. MG907003=The data cannot be copied. Check the [Data Configuration]. MG908000=Enter group code to retrieve saved data or to create a new one. MG908001=Enter a Group Name and pressing enter key. MG908002=Enter PNC# for this group code. Filling spaces for a PNC# deletes that entry. MG908003=Enter a Catalog Code (the first 3 digits) you want to register in this group. MG908100=Select a group code by sliding scroll bar and pressing enter key. MG909000=Edit scrren texts. MG909100=Enter a Screen Text (New) and press F8 key. MG910000=Select the next function by pressing an appropriate PF key. MG910100=Enter the data and press F10 key.

MG911001=To fax this Log File, select "Print>Print" from the menu.

6. EPC System Setup File Copy

6. Setup File Copy-1

Description of the functions

If you perform the reflection of the "Environmental Information" in the Setup File Copy, the environment of the terminal that performed the extract will be copied, so it is useful when creating several terminals with the same environment for the electronic catalog.

The Setup File Copy enables you to "extract" and "reflect" the environment setting information that has been setup on the EPC system and is used as follows:

(Extract)

- stores the current environment settings on the EPC system (Reflect)

- restores the environment settings on the EPC system in the case it is broken

- creates the same environment on the EPC system in the other machines

You can select the following information and "extract" and "reflect" it.

- Group code data

You can mirror the contents which set up in the [Group Setup] screen.

- Environment data

You can mirror the contents which set up in the [Data Configuration] screen.

- Screen data

You can mirror the contents which set up in the [Screen File Setup] screen.

Setup procedure

However, if you reflect the environment of the "Server" or "Standalone", the data setup is required.



Please select "Setup File Copy" of "SETUP MENU".

- * Click the "Setup File Copy" button.

To extract the Setup Information ;



- * Select the File you want to extract.
- ** In case of client, you cannot tick the "Group Code Information".
- * Select the drive where you want to store it.
- ** If you want to store it on a floppy, insert the floppy disk to the drive.
- * Click the "Extract" button to execute it.

To reflect the Setup Information ;



- * Select the File you want to reflect.
- ** In case of client, you cannot tick the "Group Code Information".
- * Select the drive where you extract it.
- ** If you want to extract it from a floppy, insert the floppy disk to the drive.
- * Click the "Reflect" button to execute it.

7. Dealing with Failures

7. Handling Failures-1

When a failure occurs, accurately understand what is going on, and you need to clarify the issues such as "whether it is necessary to deal with it immediately", "where you need to contact to" or "whether it is OK to continue a normal business operation".

If a failure occurs, deal with it according to the following procedure:



< Handling method 1 >

If a failure (error message) occurs while using the electronic catalog, check the following items, and then contact the DIST in charge.

- (1). In which screen did the failure occur? Vehicle Input, Parts Number Translation Results, ... etc.
- (2). What were you trying to do when the ... Tried to move to the next screen, trying to print... etc. failure occurred?

(3). What kind of errors occurred?

... Code=5001 error occurred...etc.



- *(1) Checking the screen name, the version of PGM used, and data Area/DVD issue.
- *(2) Checking the operation procedure
- *(3) Checking error code
- ** Pressing [Print] button will print the hard copy of the screen.

7. Handling Failures-2

< Handling method 2 >

If a hardware failure occurs in the terminal that uses the electronic catalog, after the recovery of the terminal, re-create the environment according to the following procedure.

- (1) When the operation was performed by Standalone
 - -> 2-1(p.7). Follow the Installation Flowchart (Setup at Standalone PC) and perform the program installation and data setup again.
- (2) When the operation was performed by Server/Client
 - In case of the server terminal
 - -> 3-1(p38). Follow the Installation Flowchart (Setup at Serve PC) and perform the program installation and data setup again.
 - In case of the client terminal
 - -> 3-1(p.39). Follow the Installation Flowchart (Setup at Client PC) and perform the program installation and data setup again.
 - ** If the server terminal is changed, perform the allocation of the network drive again by using the same drive.

7. New EPC Error Code List

Error Code	Workaround	Error Code	Workaround	
During your search or data setup			During printing	
5001		5001		
5002	1) If this is a PC terminal specific	5002	1) If this is a PC terminal specific	
5003	error(at certain PC terminals)	5003	error(at certain PC terminals)	
5004	Setup data at the subject PC terminal may	5004	Confirm that you can print from other	
5005	have been damaged.	5005	applications than EPC.	
5006		5006	<pre><lf printing="" successful="" was=""></lf></pre>	
5007	₹ 7	5007	Finish the EPC once and restart it.	
5008	<operated (from="" cd="" data)="" hdd="" on=""></operated>	5008	See if the same error occurs.	
5009	Re-setup the catalog data CD that has	5009	If the result is the same,	
5010	caused the subject error.	5010	please re-install the EPC program.	
5014		5011	*If the error still remains even afer	
5015		5012	re-installation, please contact us.	
5016	2) If the same kind of error occurs			
5017	at a different PC terminal		<pre><lf printig="" unsuccessful="" was=""></lf></pre>	
5018	There seems to be a possible problem		Check the printer settings.	
5019	in the setup data. Please contact us.			
5020				
5023			2) If the same kind of error occurs	
5024			at a different PC terminal	
5025			Make sure the printer power switch is on,	
5026			and confirm that you can print from	
5027			other applications than EPC.	
5011				
5012	1) If this is a PC terminal specific			
5013	error(at certain PC terminals)			
5022	Finish the EPC once and restart it.			
5028	See if the same error occurs.			
5029	If the result is the same,	<u>*When</u>	*When you contact us, please let us know*	
5030	please re-install the EPC program.	A) Displayed error code (in 4 digits)		
5031	*If the error still remains even afer		B) What you were doing when the error occurred	
5032	re-installation, please contact us.	(operations or procedures that were under way)		
5033		e.g. A screen description or search conditions		
5034	2) If the same kind of error occurs	such as VIN No or Model Code		
5035	at a different PC terminal			
5036	There seems to be a possible problem			
5037	in the setup data. Please contact us.			
5021				

Install Manual

Published JANUARY, 2016 (Ver7.0)

Edited & Published by Service Parts Engineering Administration Div.

TOYOTA MOTOR CORPORATION

ew-5epcinq@mail.toyota.co.jp